

KYOCERA Kona

User Guide



©2013 Kyocera Corporation. All Rights Reserved. Public Mobile, Everybody Talk and the Public Mobile logo are trade-marks of Public Mobile Inc. Other marks are the property of their respective owners. KYOCERA is a registered trademark of Kyocera Corporation.

Table of Contents

Get Started	1
Your Phone at a Glance	1
Set Up Your Phone.....	2
Set Up Voicemail	3
Customer Support	4
Phone Basics	5
Your Phone's Layout	6
Turn Your Phone On and Off.....	8
Battery and Charger	8
View the Display Screen.....	9
Navigate Through the Menus	11
Enter Text.....	12
Select a Text Input Mode	12
T9 Text Input.....	13
Abc Mode.....	13
Set Text Entry Options	14
Phone Calls & Settings	15
Make Phone Calls	15
Call Using the Phone Keypad	15
Call From Recent Calls	16
Call From Contacts	16
Call Using the Plus (+) Code.....	16
Call Using a Speed Dial Number.....	16
Call Using Abbreviated Dialing Features.....	17
Call a Phone Number With Pauses	18
Call a Phone Number in a Message.....	18
Call Emergency Numbers	18
Receive Phone Calls	19
End Phone Calls.....	21
Voicemail.....	21

Set Up Voicemail	21
Voicemail Notification.....	22
New Voicemail Message Alerts	22
Retrieve Your Voicemail Messages.....	22
Phone Call Options.....	23
Caller ID.....	23
Call Waiting.....	23
3-Way Calling	24
Call Forwarding.....	24
Call Setup Options.....	25
Call Answer Mode.....	25
Auto-Answer Mode	25
Auto Redial Mode	25
DTMF Tones.....	26
Voice Privacy	26
1-Touch Dialing.....	26
Call Restrictions	26
Roaming.....	26
Roaming Settings.....	27
Data Roaming.....	27
Settings.....	29
Display Settings.....	29
Set the Screensaver	29
Change the Brightness.....	30
Change the Backlight Settings	30
Set the Notification Pop-up	30
Select a Picture ID	31
Power Save Mode.....	31
Change the Wallpaper	31
Change the Clock/Calendar Display.....	31
Set a Custom Greeting.....	31
Display Language	32
Change the Phone's Menu Style.....	32

Change the Font Size	32
Sounds Settings	32
Adjust the Phone's Volume Settings	33
Silence All	33
Ringer Settings	33
Alerts Settings.....	34
Phone Setup Options	34
TTY Mode	35
Hearing Aid Device Compatibility	36
Airplane Mode.....	36
Headset Mode	36
Select a Vibration Pattern	37
Location Services.....	37
Navigation Key Shortcuts.....	37
Security Settings	38
Lock Your Phone	38
Delete Phone Content.....	39
Reset Your Phone and Phone Content	40
Security Features for Data Services.....	40
Recent Calls	42
View Recent Calls	42
The Recent Calls List.....	42
Recent Calls Icons	43
Recent Calls Thread	43
Recent Calls Details.....	43
Recent Calls Options.....	43
Make a Call From Recent Calls	44
Save the Information in Your Recent Calls	44
Save a Number From Recent Calls.....	44
Make a New Group Entry From Recent Calls.....	45
Delete Recent Calls.....	45
Call Timer.....	45
Contacts.....	47

View Contacts Entry	47
The Contacts List	47
Contacts Details	47
View Recent Calls From Contacts	48
Create a New Contacts Entry	48
Create a Contacts Entry	48
Create a Group Entry	48
Save a Number Using the Phone Keypad	49
Edit a Contacts Entry	49
Edit a Contacts Entry	49
Delete a Contacts Entry	50
Add a Number to a Contacts Entry	50
Assign a Ringer to a Contacts Entry	50
Assign a Picture to a Contacts Entry	51
Add Members to a Group Entry	51
Remove Members From a Group Entry	51
Find Contacts Entries	52
Find an Entry From Contacts	52
Find an Entry Using the Phone Keypad	52
Use Contacts Information in Other Applications	53
Assign Speed Dial Numbers	53
Secret Contacts Entries	54
Messages	55
Compose Messages	55
Access Messages	56
Threaded Messages	56
Messages Settings	57
Simple Data Exchange	59
Calendar	61
Add an Event to the Calendar	61
Add a To Do List Item to the Calendar	62
Calendar Alerts	62
View Events	63

Delete Events	63
Tools	65
Alarm	65
Voice Services	66
Automatic Speech Recognition (ASR)	66
Manage Voice Memos	69
Calculator	71
World Clock	71
Countdown Timer	72
Stopwatch	72
Bluetooth	73
Turn Bluetooth On and Off	73
Make Your Phone Discoverable	73
Bluetooth Menu	74
Pair Bluetooth Devices	74
View the Trusted Devices List	75
Send Items via Bluetooth	76
Camera	77
Take Pictures	77
Take a Picture	77
Assign Pictures	78
Camera Mode Options	78
Camera Settings	80
Camera Icons	80
Use Other Settings Menu	81
Store Pictures	81
Review Pictures in the My Photos Folder	81
My Photos Folder Options	81
Review Pictures in the Assigned Media Folder	82
Send Pictures	82
Multimedia	84
Photos	84
View Your Pictures	84

Assign Your Pictures	84
Delete Your Pictures	84
Downloaded Files	85
View Downloaded Files	85
Erase Downloaded Files	85
Preloaded Files	85
Web and Data	87
Data Services	87
Launch a Web Connection	87
Data Connection Status and Indicators	87
Browser	88
Learn to Navigate the Web	88
Browser Menu	89
Info Portal	91
Access the Info Portal	91
Notes	92
Copyrights	93
Index	94

Get Started

This section gives you all the information you need to set up your phone and use your service the first time.

[Your Phone at a Glance](#)

[Set Up Your Phone](#)


[Set Up Voicemail](#)

[Customer Support](#)

Your Phone at a Glance

The following illustration outlines your phone's primary external features.






Set Up Your Phone


You must first install and charge the battery to begin setting up your phone.

1. Install the battery.


- Hook your fingernail into the slot at the bottom of the battery cover and lift the cover off gently (Figure ①).



- Insert the battery, contacts end first, and gently press into place (Figure ②).



- Replace the cover, making sure all the locking tabs of the cover are seated with no gaps (Figure ③).



2. Charge your battery.


- Plug the USB connector into the charger/accessory jack on the lower left side of your phone.
- Plug the AC adapter into an electrical outlet.

Note: Your phone's battery should have enough charge for your phone to turn on and find a signal, set up your voicemail, and make a call. You should fully charge your battery as soon as possible.

3. Press  to turn the phone on.

Set Up Voicemail

Your phone automatically transfers all unanswered calls to your voicemail, even if your phone is in use or turned off. You should set up your voicemail and personal greeting as soon as your phone is activated. Always use a password to protect against unauthorized access.

1. From standby mode, press and hold  to dial your voicemail number.
2. Follow the system prompts to:
 - Create your password.
 - Record your name announcement.
 - Record your greeting.

Note: Voicemail Password – It is strongly recommended that you create a password when setting up your voicemail to protect against unauthorized access. Without a password, anyone who has access to your phone is able to access your voicemail messages.

For more information about using your voicemail, see [Voicemail](#).

Customer Support

Please contact Public Mobile through one of the options below:

- Use our [Support](#) page on PublicMobile.ca which has answers to a range of questions.
- Contact us by email at support@publicmobile.ca. We'll get back to you within 72 hours.
- Dial *611 from your Public Mobile phone.
- Call Customer Service at 1-855-4PUBLIC (1-855-478-2542).

For questions about the phone features, refer to the materials provided with your phone, or visit <http://www.publicmobile.ca/>.

Phone Basics

Your phone is packed with features that simplify your life and expand your ability to stay connected to the people and information that are important to you. The topics in this section will introduce the basic functions and features of your phone.

Your Phone's Layout

Turn Your Phone On and Off

Battery and Charger

View the Display Screen

Navigate Through the Menus








Enter Text

Your Phone's Layout

The illustrations and descriptions below outline your phone's basic layout.



Key Functions

- **Earpiece** lets you hear the caller and automated prompts.
- **Main Screen** displays all the information needed to operate your phone, such as the call status, the Contacts list, the date and time, and the signal and battery strength.
- **OK Key** () lets you access the phone's menus and select the highlighted choice when navigating through a menu.
- **Camera Key** () lets you access the Photos menu. Press and hold to activate the camera mode and take pictures.
- **Talk Key** () allows you to place or receive calls, answer Call Waiting, use 3-Way Calling, or activate Automatic Speech Recognition (ASR).
- **Speaker Key** () lets you place or receive calls in speakerphone mode, turn the speakerphone on and off during a call, or activate Automatic Speech Recognition (ASR).
- **Microphone** allows other callers to hear you clearly when you are speaking to them.
- **Softkeys** () let you select softkey actions or menu items corresponding to the bottom left and right lines on the screen.
- **Navigation Key** scrolls through the phone's menu options and acts as a shortcut key in standby mode. These keys can be reassigned to create customized shortcuts. See [Navigation Key Shortcuts](#).
- **Back Key** () deletes characters from the display in text input mode. When in a menu, pressing it returns you to the previous menu. This key also allows you to return to the previous screen in a data session.
- **End/Power Key** () lets you turn the phone on or off, end a call, or cancel your input and return to standby mode.
- **Keypad** lets you enter numbers, letters, and characters, and perform functions.
- **Volume Button** allows you to adjust the ringer volume in standby mode or the voice volume during a call.
- **Outer Screen** lets you monitor the phone's status and see who is calling without opening the phone.
- **Charger/Accessory Jack** allows you to connect a compatible charging cable or USB data cable (not included).
- **Camera Lens**, as part of the built-in camera, lets you take pictures.

- **Speaker** lets you hear the different ringers and sounds. The speaker also lets you hear the caller's voice in speakerphone mode.
- **Headset Jack** allows you to plug in an optional headset for convenient, hands-free conversations.
- **Internal Antennas** facilitate reception and transmission. To maximize performance, do not obstruct while using the phone.
- **Battery Cover Slot** lets you open the battery cover to replace the battery.

CAUTION! Inserting an accessory into the incorrect jack may damage the phone.


Turn Your Phone On and Off

The instructions below explain how to turn your phone on and off.

Turn Your Phone On

- Open the phone and press .

Turn Your Phone Off


- Open the phone and press and hold  for two seconds until you see the powering-down animation on the main screen.

Battery and Charger

Warning: Use only Kyocera-approved batteries and chargers with your phone. The failure to use a Kyocera-approved battery and charger may increase the risk that your phone will overheat, catch fire, or explode, resulting in serious bodily injury, death, or property damage.

Battery Capacity

Your phone is equipped with a Lithium Ion (Li-Ion) battery. It allows you to recharge your battery before it is fully drained.

For a quick check of your battery level, glance at the battery charge indicator located in the upper left side of your phone's display screen. When there are approximately five minutes of talk time left, the battery icon () turns red and the phone sounds a warning tone.

After an additional five minutes or so, the phone sounds a warning tone three times and then turns off.

Note: Long backlight settings, searching for service, vibrate mode, browser use, and other variables may reduce the battery's talk and standby times.

Tip: Watch your phone's battery level indicator and charge the battery before it runs out of power.

Install the Battery

- See [Set Up Your Phone](#).








Remove the Battery



1. Make sure the power is off so that you don't lose any stored numbers or messages.
2. Hook your fingernail into the slot at the bottom of the battery cover and lift the cover off gently.
3. Remove the battery from the phone and replace the cover.









Warning: Do not handle a damaged or leaking Li-Ion battery as you can be burned.





View the Display Screen




The status bar at the top of your phone's display screen provides information about your phone's status and options. The following tables identify the symbols you'll see on your phone's display screen.

Service Icon	Description
	Signal Strength - Your phone's current signal strength. (More bars = stronger signal.)
	No Service - Your phone cannot find a usable signal.
	Roaming - Your phone is "roaming" off the Public Mobile network.
	Data Service Available - Data service is available. When active, the icon is animated.
	Data Service Dormant - Data service is currently dormant.
	Data Service Unavailable - Data service is currently unavailable.
	Not activated - Your phone is not activated.



Status Icon	Description
	Missed Call - You have one or more missed voice calls.
	Battery - Your phone's current battery charge level. (The icon to the left shows the battery is fully charged.) The icon is animated while the battery is charging.




	Location On - Your phone's location feature is on and available for location-based services such as GPS Navigation.
	Location Off - Your phone's location feature is off. Your location is available only for 911.
	Silence All - Your phone's sound is turned off.
	Vibrate All - Your phone's sound is turned off but vibrate is turned on.
	Ringer Off - Your phone's ringer is turned off.
	1 Beep - A beep sounds when you receive an incoming call, a message, etc.
	1 Beep & Vibrate - 1 Beep and vibrate are set.
	Ringer & Vibrate - The volume level is set to between 1 and 8 and vibrate is turned on.

Messages and Alert Icon	Description
	New SMS Messages - You have one or more new SMS messages waiting.
	New MMS Messages - You have one or more new MMS messages waiting.
	New Voicemail - You have one or more new voicemail messages waiting.
	Multiple Alerts - You have different kinds of alerts waiting.

Bluetooth Icon	Description
	Visible - Your phone is discoverable by (visible to) other Bluetooth devices.
	Connected - Your phone is connected to a Bluetooth device.
	Enabled - Your phone's Bluetooth feature is enabled.

Note: The above icons will blink while your phone is communicating with a Bluetooth device.

Other Icon	Description
	TTY - Your phone is connected to a TTY device.
	Alarm - An alarm or countdown is set.

	Calendar - You have event notifications.
	HAC Enabled - Your phone's HAC (hearing aid compatibility) setting is enabled.
	Airplane Mode - Your phone is in Airplane mode.

Navigate Through the Menus

The navigation key on your phone lets you scroll through onscreen items. To navigate through a menu, press the navigation key up or down.

Many menus feature a scroll bar on the right to help you keep track of your position in the menu.

Select Menu Items

As you navigate through the menu, menu options are highlighted. Select any option by highlighting it and pressing **OK**. If the option is numbered, you can select it by pressing the corresponding number on the phone's keypad.

For example, to switch to French Menus:

1. Press **OK** to access the main menu.
2. Select **Settings** by highlighting it and pressing **OK**.
3. Select **Others** by highlighting it and pressing **OK**.
4. Select **Language** by highlighting it and pressing **OK**.
5. Select **Français** by highlighting it and pressing **OK**.

For the purposes of this guide, the above steps condense into:

- Press **OK** > **Settings** > **Others** > **Language** > **Français**.

Back Up Within a Menu

To go to the previous menu:

- Press .

To return to standby mode:

- Press .

Enter Text

You can type on your phone using various input modes.

[Select a Text Input Mode](#)

[T9 Text Input](#)


[Abc Mode](#)

[Set Text Entry Options](#)

Select a Text Input Mode

Your phone provides convenient ways to enter letters, numbers, and symbols whenever you are prompted to enter text.







1. From a screen where you can enter text, press **OPTIONS** (right softkey) to change the text mode. (If you are in the message entry screen, press **OPTIONS** [right softkey] > **Text Mode**.)
2. Select one of the following options:
 - **Abc** to enter characters by using the alphabet mode. See [Abc Mode](#).
 - **T9Word** to enter text using a predictive text system that reduces the number of key presses required while entering a word.
 - **123** to enter numeric characters.
 - **Symbols** to enter symbols.
 - **Smileys** to enter smile icons.
 - **Emoticons** to enter “emoticons.” (This is available, for example, when composing a message or when editing a Schedule or To Do description in Calendar.)
 - **Paste List** to paste copied or cut text (if applicable).
 - **Web Shortcuts** to enter Web shortcuts (for example, www., http://, or .com).
 - **Text Options** to display the text entry options menu (if applicable). See [Set Text Entry Options](#).

Tip: When entering text, press  to change the capitalization style as **Abc** > **ABC** > **abc** (ABC mode), or as **T9Word** > **T9WORD** > **T9word** (T9Word mode). The selected style is displayed in the bottom-right corner of the screen, above the right softkey label (if applicable).

T9 Text Input

T9 Text Input lets you enter text by pressing keys just once per letter. To select the **T9 Word** mode when entering text, see [Select a Text Input Mode](#).

T9 Text Input uses an intuitive word database to analyze the letters you enter and create a suitable word. (The word may change as you type.)

1. Select the **T9Word** text input mode.
2. Press the corresponding keys once per letter to enter a word. (For example, to enter the word “Bill,” press    .) (If you make a mistake, press  to erase a single character. Press and hold  to erase an entire word.)

If the word you want is not displayed after you have entered all the letters, press the navigation key to scroll through additional word selections. To accept a word and insert a space, press



Add a Word to the T9 Database


If a word you want to enter is not displayed in a T9 word choice list when you are using T9 Input, add it to the database.


1. While you are in **T9Word** mode, enter a letter. (A word choice list opens.)
2. Scroll down the list and select **<Add Word>**.
3. Enter a word and press **SAVE** (left softkey). The word will appear as an option the next time you scroll through options during T9 Text Input.

For more information about T9 Text Input, visit the Nuance website at nuance.com/t9/xt9/.

Abc Mode

In **Abc** mode, also known as multi-tap entry, you press keys one, two, three, or four times to enter the letters you see on the keypad.

By default, the first letter of a sentence is capitalized and the following letters are lowercased. To switch between lowercase and uppercase, press the  key. After a character is entered, the cursor automatically advances to the next space after two seconds or when you enter a character on a different key.

1. Select the **Abc** text input mode. See [Select a Text Input Mode](#).
2. Press the corresponding key repeatedly until the correct letter appears. For example, to enter “Abc,” press  once for “a,” twice for “b,” and three times for “c.”


Set Text Entry Options

The text entry options menu allows you to specify a suitable feature during the text entry process. Note that some of the options are applicable to **T9Word** mode only.

1. When entering text, press **OPTIONS** (right softkey) > **Text Options**.

– or –

From standby mode, press  > **Settings** > **Text Entry**.

2. Highlight an option and press .
- **Word Complete** to suggest possible words based on letters you have entered.
- **Next Word Complete** to automatically display the word that may follow the current text input.
- **Phrase Complete** to set the phone to predict possible phrases after one word with a space is entered.
- **Word Scan** to allow the predictive text input system to recognize words by searching Contacts.
- **Word Choice List** to select whether to display the word choice list.
- **Input Language** to select the language to enter (English or French).
- **My Words** to edit or delete custom words you have added to the predictive text database.
 - **Add Word** to store words that you frequently use.
- **Select Text** to select text for copying, cutting or adding (if applicable).
- **Delete All** to delete all text (if applicable).
- **Help** to view the T9 instructions.

Phone Calls & Settings

With the network and your phone's calling feature, you can enjoy clear calling across the country. This section explains the features related to phone calls.

[Make Phone Calls](#)

[Receive Phone Calls](#)

[End Phone Calls](#)

[Voicemail](#)

[Phone Call Options](#)

[Call Setup Options](#)

[Roaming](#)

Make Phone Calls

There are several convenient ways to place calls from your phone.

[Call Using the Phone Keypad](#)

[Call From Recent Calls](#)

[Call From Contacts](#)

[Call Using the Plus \(+\) Code](#)

[Call Using a Speed Dial Number](#)

[Call Using Abbreviated Dialing Features](#)

[Call a Phone Number With Pauses](#)

[Call a Phone Number in a Message](#)

[Call Emergency Numbers](#)

Call Using the Phone Keypad


The most "traditional" way to place a call is by using the phone's keypad.

1. Enter a phone number from standby mode. (If you make a mistake while dialing, press



to erase the numbers.)

2. Press  or .

3. Press  when you are finished.

Call From Recent Calls

Place a call to the numbers in your recent calls.

1. From standby mode, press **RECENT CALLS** (left softkey).

– or –

Press  > **Recent Calls**.


2. Highlight an entry and press .

Tip: To redial your last outgoing call, press  twice.



Note: You cannot make calls from Recent Calls to entries identified as **Unknown**, **Number Restricted**, or **Number not Available**.

Call From Contacts

Place a call to the numbers stored in your Contacts.



1. From standby mode, press **CONTACTS** (right softkey).
2. Highlight the entry you want to call.
3. Press  to dial the entry's default phone number.

– or –

To dial another number from the same entry, press  to select the entry, highlight a number, and then press .

Call Using the Plus (+) Code

When placing international calls, use Plus Code Dialing to automatically enter the international access code for your location (for example, 011 for international calls made from Canada).

1. Press and hold  to display “+” on your phone screen.
2. Enter the country code and phone number, and then press . (The phone automatically prepends the access code for international dialing, followed by the country code and phone number.)

Call Using a Speed Dial Number

You can store up to 98 numbers in your phone's speed dial memory to make contacting friends and family easier.

You must have already assigned a speed dial number to an existing phone number. See [Assign Speed Dial Numbers](#).

To use speed dial for locations 2-9:

- ▶ From standby mode, press and hold the appropriate key for approximately two seconds.

To use speed dial for locations 10-99:

- ▶ From standby mode, enter a two-digit speed dial number, and then press .



The display confirms that the number has been dialed when it shows “Connecting...”

Call Using Abbreviated Dialing Features

Abbreviated Dialing is similar to speed dialing. You can use either of the following abbreviated dialing features.

- **Contacts Match** - Retrieve any number saved in your Contacts by entering four or more digits of any part of the number.
- **Prepend** - Prepend the first five or six digits (for example, the area code and prefix) to any four or five digits you enter.

To activate the Prepend feature:

1. Press  > **Settings** > **Others** > **Call Setup** > **Abbrev. Dial**.
2. Select **Prepend** > **On**.
3. Enter a five- or six-digit number and press .



To place a call using Abbreviated Dialing:

1. Enter the four or more digits of any part of a Contacts entry's phone number to use the Contacts Match feature.

– or –

Enter the last four or five digits of the number to use the Prepend feature.

Note: Contacts Match will not retrieve numbers if you enter 911 or reserved three-digit service numbers such as 611.

2. Press  to call the displayed number. (If there are two or more matched numbers in your Contacts, a list is displayed. Highlight the name or the phone number you want to call, and then press  to place a call.)

Call a Phone Number With Pauses


You can dial or save phone numbers with pauses for use with automated systems, such as voicemail or credit card billing numbers.

There are two types of pauses available on your phone:

- **Hard Pause** sends the next set of numbers when you press **SEND TONES** (left softkey).
- **2-Sec. Pause** automatically sends the next set of numbers after two seconds.

Note: You can have multiple pauses in a phone number and combine two-second and hard pauses.

To dial or save phone numbers with pauses:

1. Enter all or part of a number.
2. Press **OPTIONS** (right softkey) > **Hard Pause** or **2-Sec. Pause**.
3. Enter additional numbers.
4. Press  to dial the number.



– or –

Press **OPTIONS** (right softkey) > **Save**. (You can save to a new or existing Contacts entry.)

Note: When dialing a number with a hard pause, press **SEND TONES** (left softkey) to send the next set of numbers.

Call a Phone Number in a Message

You can place a call to a number that appears in a message.

1. Press  > **Messages** > **Messages**.
2. Select a message with the number you want to call and press .


For more information on utilizing the information in a message, see [Simple Data Exchange](#).

Call Emergency Numbers

You can place calls to 911 even if your phone is locked or your account is restricted.

► Press    .




Note: After you have placed an emergency call, your phone automatically enters the Emergency Mode.

During an emergency call, press **OPTIONS** (right softkey) to display your options. Highlight an option and press .

- **Transfer Audio** to switch the call to an external device (if applicable).
- **Contacts** to show the Contacts list.
- **Voice Memo** to record the other party's voice.
- **Phone Info** to display information about your phone.

Tip: Press **MY PHONE#** (left softkey) to display your phone number during an emergency call.

To exit emergency mode:

1. Press  to end a 911 call.
2. Press  .

Enhanced 911 (E911) Information

This phone features an embedded Global Positioning System (GPS) chip necessary for utilizing E911 emergency location services where available.

When you place an emergency 911 call, the GPS feature of your phone seeks information to calculate your approximate location. Depending on several variables, including availability and access to satellite signals, it may take up to 30 seconds or more to determine and report your approximate location.

Important: Always report your location to the 911 operator when placing an emergency call. Some designated emergency call takers, known as Public Safety Answering Points (PSAPs) may not be equipped to receive GPS location information from your phone.

Receive Phone Calls

You can select the most convenient way to respond to a call.

Your phone notifies you of incoming calls in the following ways:


- The phone rings or vibrates.
- The backlight illuminates.
- The screen displays an incoming call message.

If the incoming call is from a number stored in your Contacts, the entry's name is displayed. The caller's phone number may also be displayed, if available.

Note: If your phone is turned off, all calls automatically go to voicemail.

Note: Your phone will answer an incoming call by opening the phone by default. To change the setting, see [Call Answer Mode](#).


Answer an Incoming Call

- ▶ Press  to answer an incoming call. (Depending on your settings, you may also answer incoming calls by pressing other keys. See [Call Answer Mode](#).)

Answer an Incoming Call in Speakerphone Mode

- ▶ Press .



Mute the Ringer and Stop the Vibration

- ▶ Select **Silence** on the screen.
— or —
Press  or the volume button up or down.

Send an Incoming Call to Voicemail

- ▶ Select **Send to Voicemail** on the screen.


Reject an Incoming Call

- ▶ Press .
- or —
Press and hold .

Reject an Incoming Call and Send a Message

- ▶ Select **Ignore with Text**.


In-call Options

Pressing **OPTIONS** (right softkey) during a call displays a list of available in-call features. To select an option, highlight the option and press .

- **Transfer Audio** to switch the call to a Bluetooth device (if applicable).
- **Save** to save the current call's phone number in your Contacts.
- **Contact Details** to display information about the caller stored in your Contacts (if applicable).

- **Main Menu** to display the phone's main menu.
- **3-Way Call** to open a call with two other parties.
- **Contacts** to display your Contacts list.
- **Voice Memo** to record the other party's voice.
- **Phone Info** to display information about your phone.

Further options may also be available.

- ▶ Press **MUTE/UNMUTE** (left softkey) to mute/unmute the microphone.
- ▶ Press the volume button up or down to adjust the receiver volume.
- ▶ Press  to turn the speaker on. Press again to turn it off.

Warning: Because of higher volume levels, do not place the phone near your ear during speakerphone use.

End Phone Calls

- ▶ Press .

After you have finished your call, the phone will display the caller's name (if already in your Contacts), phone number (if available), and the duration of the call. Pressing **OPTIONS** (right softkey) will display the Recent Call History options. See [Recent Calls Options](#) for details.

Voicemail

Your phone automatically transfers all unanswered calls to your voicemail, even if your phone is in use or turned off. Set up your voicemail account and retrieve your messages.

[Set Up Voicemail](#)


[Voicemail Notification](#)

[New Voicemail Message Alerts](#)

[Retrieve Your Voicemail Messages](#)

Set Up Voicemail

You should set up your Voicemail and personal greeting as soon as your phone is activated. Always use a password to protect against unauthorized access.

1. Press and hold  in standby mode to dial your voicemail number.
2. Follow the system prompts to:


- Create your password.
- Record your name announcement.
- Record your greeting.

Important: **Voicemail Password** – It is strongly recommended that you create a password when setting up your voicemail to protect against unauthorized access. Without a password, anyone who has access to your phone is able to access your voicemail messages.

Voicemail Notification

There are several ways your phone alerts you to a new message.


You will be notified of a new voicemail:

- By displaying a message on the screen.
- By sounding the assigned ringer type.
- By displaying  at the top of the screen.

New Voicemail Message Alerts

When you receive a new voicemail message, your phone alerts you and prompts you to call your voicemail.

To call your voicemail from the notification screen:


1. Press .
2. Enter your voicemail password if prompted.
3. Follow the voice prompts to listen to and manage your voicemail messages.

Note: Your phone accepts messages even when it is turned off. However, your phone notifies you of new messages only when it is turned on and you are in a Public Mobile service area.

Retrieve Your Voicemail Messages

You can review your messages directly from your wireless phone or from any other touch-tone phone.

Use Your Phone to Access Your Messages

1. Press and hold .
- or –

From standby mode, press  > **Messages** > **Voicemail**.

2. Enter your voicemail password if prompted.
3. Follow the voice prompts to listen to and manage your voicemail messages.

Note: You are charged for airtime minutes when you are accessing your voicemail from your wireless phone.

Use Another Phone to Access Messages

1. Dial your wireless phone number.
2. When your voicemail answers, press the pound key (#).
3. Enter your password.

Phone Call Options

Your phone provides many useful features and options to help you make the most of your calling experience.

Caller ID






Call Waiting

3-Way Calling

Call Forwarding

Caller ID

Caller ID identifies a caller before you answer the phone by displaying the number of the incoming call. If you do not want your number displayed when you make a call, follow these steps.

1. Enter    .
2. Enter the number you want to call.
3. Press .

Call Waiting

When you are on a call, Call Waiting alerts you to incoming calls by sounding a beep. Your phone's screen informs you that another call is coming in and displays the caller's phone number (if available).

To respond to an incoming call while you are on a call:





- ▶ Press . (This puts the first caller on hold and answers the second call.)

To switch back to the first caller:

- ▶ Press  again.

3-Way Calling

With 3-Way Calling, you can talk to two people at the same time. When using this feature, the normal airtime rates will be charged for each of the two calls.

1. Enter a number and press .
2. Once you have established the connection, press . (This puts the first caller on hold.)
3. Select **Contacts**, **Recent History**, or **Enter Phone#**.
4. Select a number from your Contacts or Recent History, or enter a number directly, and then press .
5. When you're connected to the second party, press  again to begin your 3-way call.





If one of the people you called hangs up during your call, you and the remaining caller stay connected. If you initiated the call and are the first to hang up, all callers are disconnected.

Call Forwarding






Call Forwarding lets you forward all your incoming calls to another phone number—even when your phone is turned off. You can continue to make calls from your phone when you have activated Call Forwarding.

Note: You are charged a higher rate for calls you have forwarded.

To activate Call Forwarding:

1. Enter   .
2. Enter the area code and phone number to which you want your calls forwarded.
3. Press . (You will hear a tone to confirm the activation of Call Forwarding.)

To deactivate Call Forwarding:

1. Enter    .
2. Press . (You will hear a tone to confirm the deactivation.)

Call Setup Options

Various call-related settings are available. You can configure call options through your phone's Call Setup menu.

Call Answer Mode

Auto-Answer Mode

Auto Redial Mode

DTMF Tones

Voice Privacy

1-Touch Dialing

Call Restrictions

Call Answer Mode

Select how to answer incoming calls on your phone.

1. Press **OK** > **Settings** > **Others** > **Call Setup** > **Call Answer**.
2. Select **Talk Key**, **Any Key**, or **Flip Open**.

Auto-Answer Mode

Set your phone to automatically pick up incoming calls. Remember, your phone will answer calls in auto-answer mode even if you are not present.

1. Press **OK** > **Settings** > **Others** > **Call Setup** > **Auto-Answer**.
2. Highlight an option and press **OK**.
 - **Hands-free** to answer calls automatically when the phone is connected to an optional headset or hands-free device.
 - **Speakerphone** to answer calls automatically in speakerphone mode.
3. Highlight the time you would like your phone to wait before answering and press **OK**.


Auto Redial Mode

With Auto Redial enabled, your phone will automatically redial the number it failed to connect to.

1. Press **OK** > **Settings** > **Others** > **Call Setup** > **Auto Redial**.
2. Select **On** or **Off**.


DTMF Tones

Follow the steps below if you need to change the DTMF tones.

1. Press  > **Settings** > **Others** > **Call Setup** > **DTMF Tones**.
2. Select either **Short** or **Long**.


Voice Privacy

You can enable the enhanced privacy mode.

1. Press  > **Settings** > **Others** > **Call Setup** > **Voice Privacy**.
2. Select **On** or **Off**.


1-Touch Dialing

This feature allows you to quickly call a Contacts phone number without pressing the Talk key.

1. Press  > **Settings** > **Others** > **Call Setup** > **1-Touch Dialing**.
2. Select **On** or **Off**.

Call Restrictions

You can restrict the phone calls your phone can make and receive. Emergency calls will not be affected by this restriction setting.

1. Press  > **Settings** > **Others** > **Call Setup** > **Call Restrictions**.
2. Enter your lock code and press **CONTINUE** (left softkey).
3. Select **Outgoing Calls** or **Incoming Calls**.
4. Select **Allow All**, **Allow Contacts**, or **Allow None**.


Roaming

Roaming is the ability to make or receive calls and access data services when you're off the home network.

Roaming Settings

Data Roaming

Roaming Icon

Your phone's display screen always lets you know when you're off the Public Mobile network. Anytime you are roaming, the phone displays the roaming icon (.

Roaming on Other Network

When you're roaming on other networks, your call quality and security will be similar to the quality you receive when making calls on the Public Mobile network. However, you may not be able to access certain features, such as data services, depending on the available network.

Note: If you're on a call when you leave the home network, your call is dropped. If your call is dropped in an area where you think network service is available, turn your phone off and on again to reconnect to the network.

Check for Voicemail Messages While Roaming

When you are roaming off the Public Mobile network, you may not receive on-phone notification of new voicemail messages. Callers can still leave messages, but you will need to periodically check your voicemail for new messages if you are in a roaming service area for an extended period of time.


1. Dial your ten-digit wireless phone number.
2. When you hear your voicemail greeting, press the pound key (#).
3. Enter your password at the prompt and follow the voice prompts.

When you return to the Public Mobile network, voicemail notification will resume as normal.

Roaming Settings

Your phone allows you to control your roaming capabilities. By using the Roaming menu option, you can determine which signals your phone accepts.

To set the roaming mode:

1. Press  > **Settings** > **Others** > **Roaming** > **Set Mode**.
2. Select an option:
 - **Home Only** to access only the Public Mobile network and prevent roaming on other networks.
 - **Automatic** to seek service on the Public Mobile network. When Public Mobile service is unavailable, the phone searches for an alternate service.

Data Roaming

The data roaming option allows you to send and receive data while you're off the Public Mobile network. All applicable charges apply for accessing the available network.

To turn data roaming on or off:

1. Press  > **Settings** > **Others** > **Roaming** > **Data Roaming**.

2. Select **On** or **Off**.

Settings

This section provides an overview of items you can change using your phone's settings menus.

Display Settings

Sounds Settings

Phone Setup Options

Security Settings

Display Settings

Adjusting your phone's display settings not only helps you see what you want, they can also help increase battery life.

Set the Screensaver

Change the Brightness

Change the Backlight Settings

Set the Notification Pop-up

Select a Picture ID

Power Save Mode

Change the Wallpaper

Change the Clock/Calendar Display

Set a Custom Greeting

Display Language

Change the Phone's Menu Style

Change the Font Size

Set the Screensaver

You can set a screensaver to display while in standby mode.

To set the screensaver:

1. Press  > **Settings** > **Display** > **Screensaver** > **Screensaver**.

2. Select a screen saver option (**No Image**, **Downloaded**, or **Preloaded**) and press **OK**.
3. Select a screen saver you want to display on the screen.

To set the screensaver timer:

1. Press **OK** > **Settings** > **Display** > **Screensaver** > **Screensaver Timer**.
2. Select your desired timeout setting and press **OK**.

Change the Brightness

You can adjust the brightness on the main screen.

1. Press **OK** > **Settings** > **Display** > **Brightness**.
2. Highlight a brightness level and press **OK** twice.

Change the Backlight Settings

Select how long the display screen remains backlit after any keypress is made.

To change the main screen backlight setting:

1. Press **OK** > **Settings** > **Display** > **Main Screen** or **Outer Screen** > **Backlight**.
2. Select **Backlight Dim** or **Backlight Off**.
 - If you select **Backlight Dim**, select **Always Bright**, **Always Dim**, or a preset length of time to elapse before the screen backlight dims.
 - If you select **Backlight Off**, select a preset length of time to elapse before the screen and keypad backlights turn off. (When you select **Always Bright** for the **Backlight Dim** setting in step 2, the keypad backlight will turn off after about one minute.)

Note: Long backlight settings reduce the battery's talk and standby times.

Set the Notification Pop-up

This option allows you to enable or disable notification pop-up when you receive a new notification (except for incoming call and alarm) while an application is running.

1. Press **OK** > **Settings** > **Display** > **Notification**.
2. Select **Enable Pop-up** or **Disable Pop-up**.

Tip: If you select **Disable Pop-up**, you will see only a notification icon. (The notification pop-up will not appear while an application is running.)

Select a Picture ID

You can select an image as a picture ID.

1. Press **OK** > **Settings** > **Display** > **Picture ID**.
2. Select **Contact**, **Unsaved Numbers**, or **Private / Unknown**.
 - If you select **Contact**, select an entry.
3. Select a picture ID option and press **OK**.
4. Select an image and press **OK** to assign it.

Power Save Mode

This feature helps conserve your battery power by automatically adjusting the backlight setting of your phone.

1. Press **OK** > **Settings** > **Display** > **Power Save Mode**.
2. Select **On**. (Select **Off** to deactivate this feature.)
3. Read the message and press **CONTINUE** (left softkey).

Change the Wallpaper

You can set a wallpaper to display while in standby mode.

1. Press **OK** > **Settings** > **Display** > **Main Screen** or **Outer Screen** > **Wallpaper**.
2. Select a wallpaper option by pressing the navigation key up or down, and select a wallpaper.

Change the Clock/Calendar Display

Select a clock/calendar display on the main screen in standby mode.

1. Press **OK** > **Settings** > **Display** > **Main Screen** or **Outer Screen**.
2. Select **Clock/Calendar** (for main screen) or **Clock** (for outer screen).
3. Select an option and press **OK**.
4. Press **OK** (left softkey) to confirm.

Set a Custom Greeting

You can display your own custom greeting in standby mode.

1. Press **OK** > **Settings** > **Display** > **Main Screen** or **Outer Screen** > **Personal Banner** > **Custom**.
2. Enter a custom greeting and press **OK**.
3. Press **DONE** (left softkey) to save your greeting.

Display Language

You can choose to display your phone's onscreen menus in English or in French.

1. Press **OK** > **Settings** > **Others** > **Language**.
2. Select **English** or **Français**.

Change the Phone's Menu Style

Choose the layout of your phone's menu.

1. Press **OK** to display the main menu.
2. Press **OPTIONS** (right softkey) > **Grid View** or **List View** to change the menu style.

Change the Font Size

Adjust the font size for the main screen. This setting does not affect all screens.

- Press **OK** to display the main menu, and then press **OPTIONS** (right softkey) > **Large Font** or **Normal Font**.

— or —

1. Press **OK** > **Settings** > **Others** > **Accessibility** > **Font Size**.
2. Highlight a font size. You can see the current and new font sizes in the display window above the menu.
3. If you are satisfied with the font size, press **SAVE** (left softkey).

Sounds Settings

Adjust your phone's sounds settings to suit your needs and your environment.

Adjust the Phone's Volume Settings

[Silence All](#)

[Ringer Settings](#)

[Alerts Settings](#)

Settings

32

Adjust the Phone's Volume Settings

You can separately adjust the volume of various sounds your phone makes.

1. Press **OK** > **Settings** > **Sounds** > **Volume**.
2. Select **Ringer Volume**, **Keypad Volume**, **Earpiece Volume**, **Auto Volume**, or **Power On/Off Volume**.
 - If you select **Auto Volume**, select **On** or **Off**.
3. Select a volume level and press **OK**.

Tip: You can adjust the ringer volume in standby mode or during an incoming call and the volume during playback by using the volume button.

Silence All

The Silence All option allows you to mute all sounds without turning your phone off.

To activate Silence All:

- ▶ Press and hold the volume button down in standby mode. (The screen will display "Silence All.")

To deactivate Silence All:

- ▶ Press the volume button up repeatedly to select a volume level.

Ringer Settings

Ringers Settings help you identify incoming calls and messages. You can assign ringers to individual Contacts entries, types of calls, and messages.

Select Ringers for Incoming Calls and Messages

1. Press **OK** > **Settings** > **Sounds** > **Ringers** > **Incoming Calls** or **Messages**.
2. Select **Contacts**, **Unsaved Numbers**, or **Private / Unknown**.
 - If you select **Contacts**, select **All Contacts**, or select **One Contact** and then select an entry.
3. Select a ringer option by pressing the navigation key up or down, and then select a ringer.

Tip: Ringers can be assigned from the Contacts menu. See [Assign a Ringer to a Contacts Entry](#).

Select Ringers for Voicemail, Calendar, Power On, or Power Off.

1. Press **OK** > **Settings** > **Sounds** > **Ringers**.
2. Select **Voicemail**, **Calendar**, **Power On**, or **Power Off**.
3. Select a ringer option by pressing the navigation key up or down, and then select a ringer.

Alerts Settings

You can set your phone to alert you when you change service areas, connect or disconnect a call, as well as other options.

1. Press **OK** > **Settings** > **Sounds** > **Alerts**.
2. Select an option and press **OK**.
 - **Call Connect Alert** to sound an alert when a call is connected.
 - **Back to Top Alert** to sound an alert when you return to the top of a menu.
 - **Missed Call Alert** to sound an alert when you have missed a call.
 - **Drop Alert** to sound an alert when a call is dropped.
 - **Minute Alert** to sound an alert every minute during a call.
 - **Roam/Svc Alert** to sound an alert when leaving a service area and entering a roaming service area.
 - **Voice Privacy Alert** to sound an alert when voice privacy is activated during a call.
 - **Voicemail Alert** to sound an alert when you receive a voicemail.
 - **MMS Alert** to sound an alert when you receive a MMS message.
 - **Text Alert** to sound an alert when you receive a text message.
 - **Vibrate Alert** to set vibration alert when you receive messages.
3. Select **On** or **Off**.

Phone Setup Options

Configure your phone to your convenience.

[TTY Mode](#)

[Hearing Aid Device Compatibility](#)

Airplane Mode

Headset Mode

Select a Vibration Pattern

Location Services



Navigation Key Shortcuts

TTY Mode

A TTY (also known as a TDD or Text Telephone) is a telecommunications device that allows people who are deaf, hard of hearing, or who have speech or language disabilities to communicate by telephone.

Your phone is compatible with select TTY devices. Please check with the manufacturer of your TTY device to ensure that it is compatible with digital cell phones. Your phone and TTY device will connect via a special cable that plugs into your phone's headset jack. If this cable was not provided with your TTY device, contact your TTY device manufacturer to purchase the connector cable.

To turn TTY Mode on or off:

1. Press  > **Settings** > **Others** > **Accessibility** > **TTY**.
2. Read the message and press .
3. Select one of the following options:
 - **TTY Off** to disable TTY mode.
 - **TTY VCO** to enable TTY mode in Voice Carry Over mode, which allows you to send voice and receive text during a call.
 - **TTY HCO** to enable TTY mode in Hearing Carry Over mode, which allows you to send text and receive voice during a call.
 - **TTY Full** to enable all TTY settings. You can send and receive text during a call.

Note: When enabled, TTY mode may impair the audio quality of non-TTY devices connected to the headset jack.



Warning: **911 Emergency Calling**

It is recommended that TTY users make emergency calls by other means, including Telecommunications Relay Services (TRS), analog cellular, and landline communications. Wireless TTY calls to 911 may be corrupted when received by public safety answering points (PSAPs), rendering some communications unintelligible. The problem encountered appears related to

software used by PSAPs. This matter has been brought to the attention of the FCC, and the wireless industry and the PSAP community are currently working to resolve this.



Hearing Aid Device Compatibility

Your phone has been tested and rated for hearing aid device compatibility. To use this function effectively, set the **Hearing Aid** option to **On**.

1. Press  > **Settings** > **Others** > **Accessibility** > **Hearing Aid**.
2. Read the disclaimer and press .
3. Select **On** or **Off**.
 - **On** to use a hearing aid device with your phone.
 - **Off** to use your phone without a hearing aid device.

Airplane Mode



Airplane Mode allows you to use many of your phone's features, such as games and voice memos, when you are on an airplane or in any other area where making or receiving calls or data is prohibited. When you set your phone to Airplane Mode, it cannot send or receive any calls or access online information.

1. Press  > **Settings** > **Others** > **Airplane Mode**.
2. Read the disclaimer and press .
3. Select an option from the following:
 - **On** to activate Airplane Mode. Airplane Mode will be deactivated when you turn the phone off.
 - **Off** to deactivate Airplane Mode.
 - **On Power-up** to activate Airplane Mode each time you turn the phone on.

While in Airplane Mode, your phone's screen will display the airplane mode icon .

Headset Mode



Set the sound output destination of incoming ringer on your phone.

1. Press  > **Settings** > **Others** > **Headset Mode**.
2. Select an option and press .

- **Normal** to play the ringer for incoming calls through both the headset and the speaker.
- **Headset Only** to play the ringer for incoming calls only through the headset.

Select a Vibration Pattern



You can select vibration patterns for incoming calls, messages, alarms, and scheduled events.



1. Press  > **Settings** > **Others** > **Accessibility** > **Vibrate Type**.
2. Select **Incoming Calls**, **Voicemail**, **Messages**, or **Alarm/Calendar**.
3. Highlight a vibration pattern and press .

Location Services


Your phone's built-in GPS capability gives you access to a number of location-based services. Before using any of the location-based services, you must turn on your phone's location feature.

To enable your phone's location feature:

1. Press  > **Settings** > **Others** > **Location** > **On/Off**. (You will see the Location disclaimer.)
2. Read the disclaimer and press .
3. Select **On**.

When the Location feature is on, your phone's standby screen will display the  icon. When Location is turned off, your phone will display the .

To send the GPS log to other devices:

1. Press  > **Settings** > **Others** > **Location** > **NMEA Output**.
2. Select **USB**.

Note: Turning Location on will allow the network to detect your position using GPS technology, making some Public Mobile applications and services easier to use. Turning Location off will disable the GPS location function for all purposes except 911, but will not hide your general location based on the cell site serving your call. No application or service may use your location without your request or permission. GPS-enhanced 911 is not available in all areas.

Navigation Key Shortcuts

You can use the navigation keys as shortcuts to access specific menu items directly from standby mode. You can reassign the default shortcuts to the menu items you choose.

1. Press **OK** > **Settings** > **Others** > **Navigation Keys**.
2. Highlight the navigation key you wish to reassign and press **OK**.
3. Using the navigation key or your keypad, highlight a function.
4. Press **ASSIGN** (left softkey) to save. (For options with submenu levels, such as Settings, you can assign submenu options by navigating to the desired option before pressing **ASSIGN** [left softkey].)

Security Settings

The Security settings menus let you set phone security, lock code, and more.

[Lock Your Phone](#)

[Delete Phone Content](#)

[Reset Your Phone and Phone Content](#)

[Security Features for Data Services](#)

Lock Your Phone

When your phone is locked, you can only make calls to 911.

1. Press **OK** > **Settings** > **Lock Phone**.
2. Enter your lock code and press **CONTINUE** (left softkey).
3. Select **Lock Now**.


Tip: The first time you access the Lock Phone menu, you will be advised to change the default lock code by pressing **CHANGE** (left softkey). Enter and re-enter your new lock code to proceed. For details, see [Change the Lock Code](#).

Unlock Your Phone

1. From standby mode, press **UNLOCK** (left softkey).
2. Enter your lock code and press **CONTINUE** (left softkey).

Change the Lock Code



1. Press **OK** > **Settings** > **Lock Phone**.
2. Enter your lock code and press **CONTINUE** (left softkey).
3. Select **Change Lock Code**.

4. Enter your lock code and press **CONTINUE** (left softkey).
5. Re-enter your new lock code and press **SAVE** (left softkey). (You will be prompted to create a lock code hint to help you remember your new lock code.)
6. If you want to create a lock code hint, press **YES** (left softkey). Enter a hint and press .

— or —

Press **NO** (right softkey) to return to the previous menu.

To edit or delete a lock code hint:

1. Press  > **Settings** > **Lock Phone**.
2. Enter your lock code and press **CONTINUE** (left softkey).
3. Select **Lock Code Hint**.
4. Edit the hint and press .



— or —

Delete the hint by pressing  and press .

Tip: If you can't recall your lock code, try using the last four digits of your wireless phone number or check your lock code hint.

Delete Phone Content

You can quickly and easily delete all the content that you have created or stored in your phone.


1. Press  > **Settings** > **Reset/Delete**.
2. Enter your lock code and press **CONTINUE** (left softkey).
3. Select **Delete Stuff**.
4. Highlight an option and press .
 - **Messages** to delete all messages.
 - **Call Logs** to delete all call history from the phone.
 - **Browser Cookies and Cache** to delete all Web cookies and all Web cache memory saved in the phone.
 - **Downloaded Content** to delete all data downloaded to your phone.

- **Contacts** to delete all of your Contacts including speed dial numbers saved in your Contacts.
- **Voice Memo** to delete all voice data and call memos saved in the phone.
- **My Photos** to delete all pictures stored in My Photos.
- **All Stuff** to delete all user-added data.

5. Read the message and press **DELETE** (left softkey).

Reset Your Phone and Phone Content

This option lets you clear different types of personal information stored on your phone, reset your phone to factory settings, or both.

1. Press  > **Settings** > **Reset/Delete**.
2. Enter your lock code and press **CONTINUE** (left softkey).
3. Highlight an option and press .
 - **Reset Settings** to restore all the factory defaults, including ringer types and display settings. Contacts, Recent Calls, Calendar, and Messages are not affected.
 - **Reset Phone** to reset all settings and erase all data on your phone.
4. Read the message and press the left softkey (**RESET SETTINGS** or **RESET PHONE**).


Security Features for Data Services

You can turn on or off your phone's data services.

Enable Data Services

Although your phone's data services are turned off by default, you may enable them at any time.


To enable data services:

1. Press  > **Settings** > **Others** > **Data** > **Data Off**. (A message is displayed.)
2. Press **YES** (left softkey) to enable data services.

Disable Data Services

You can disable data services again without turning off your phone; however, you will not have access to all data services, including Web and messaging. Disabling data services will avoid any charges associated with these services. While signed out, you can still place or receive phone calls, check voicemail, and use other voice services.

To disable data services:

1. Press  > **Settings** > **Others** > **Data** > **Data On**.
2. Read the disclaimer and press **DISABLE** (right softkey) to sign out.

Net Guard

The Net Guard helps you avoid accidental connections when you connect to the Web.

To enable or disable Net Guard:

► Press  > **Settings** > **Others** > **Data** > **Net Guard**.

- **On** to activate the Net Guard.
- **Off** to deactivate the Net Guard.

Note: When enabled, Net Guard appears only once as long as you have not turned the phone off and on.

Recent Calls

Recent Calls keeps track of the calls placed, received, and missed on your phone.

[View Recent Calls](#)

[Recent Calls Options](#)

[Make a Call From Recent Calls](#)

[Save the Information in Your Recent Calls](#)

[Delete Recent Calls](#)

[Call Timer](#)

View Recent Calls

Recent Calls is a list of the last 60 incoming, outgoing, or missed phone calls. Recent Calls makes redialing fast and easy. It is continually updated as new numbers or entries are added to the beginning of the list and the oldest entries are removed from the bottom of the list.

Each entry contains the phone number (if available) and Contacts entry name (if the number is in your Contacts). Duplicate calls (calls from the same number) may appear only once on the list.

[The Recent Calls List](#)

[Recent Calls Icons](#)

[Recent Calls Thread](#)

[Recent Calls Details](#)

The Recent Calls List

The recent calls list displays your recent history at a glance.

► From standby mode, press **RECENT CALLS** (left softkey).


— or —

Press  > **Recent Calls**.


Note: Recent Calls records only calls that occur while the phone is turned on. If a call is received while your phone is turned off, it will not be included in Recent Calls.

Recent Calls Icons

You can determine if an entry was an incoming, outgoing, or missed call from the icons shown below.

 = Incoming Call

 = Outgoing Call

 = Missed Call

Recent Calls Thread

The Recent Calls thread screen shows all history for a selected entry. You can also keep track of all the messages you have sent and received for the selected entry.

To display a Recent Calls thread:

1. From standby mode, press **RECENT CALLS** (left softkey).
2. Highlight an entry and press **OK**.

Recent Calls Details

You can see further details on the call history from the Recent Calls thread screen.

To display Recent Calls details:

1. From standby mode, press **RECENT CALLS** (left softkey).
2. Highlight an entry from the list and press **OK**. The Recent Calls thread is displayed.
3. Highlight an entry and press **OK**.

An onscreen menu may also be available according to the type of call. See [Recent Calls Options](#).

Recent Calls Options


You may see several menu items on the onscreen menu. Press **OPTIONS** (right softkey) for additional options.

- **Call** to call the selected entry.
- **Send Message** to send a message to the selected entry.
- **New Group** to create a new group entry. See [Create a Group Entry](#).

- **Contact Details** to display information about the entry if it has already been saved in your Contacts.
- **Save Contact** to save a phone number. See [Save a Number From Recent Calls](#).
- **Delete** to delete the entry.
- **Delete All** to delete all Recent Calls entries. See [Delete Recent Calls](#).
- **Prepend** to add numbers to the beginning of the selected number.
- **View Call Timer** to see the duration of the different types of calls on the phone. See [View Call Timer](#).

Make a Call From Recent Calls

You can make a call from your Recent Calls.

1. From standby mode, **RECENT CALLS** (left softkey).
2. Highlight an entry and press .

Note: You cannot make calls from Recent Calls to entries identified as **Unknown**, **Number Restricted**, or **Number not Available**.

Save the Information in Your Recent Calls

You can save the information which appears in your Recent Calls to your Contacts.

[Save a Number From Recent Calls](#)


[Make a New Group Entry From Recent Calls](#)

Save a Number From Recent Calls

You can easily save a number from your Recent Calls to your Contacts.

1. From standby mode, **RECENT CALLS** (left softkey).
2. Highlight an entry and press **OPTIONS** (right softkey) > **Save Contact**.
3. Select **New Entry** or **Existing Entry**.
4. If **New Entry** was selected, select a number type, and then enter the new entry name.

– or –

If **Existing Entry** was selected, select an existing entry to which you want to save the number, and then highlight a number type and press .

5. Press **DONE** (left softkey) to save the entry.

Make a New Group Entry From Recent Calls

You can create a new group from your Recent Calls and save it to your Contacts.

1. From standby mode, press **RECENT CALLS** (left softkey) > **OPTIONS** (right softkey) > **New Group**.
2. Read the message and press **START** (left softkey).
3. Highlight an entry you want to add to a group and press **OK**. A check mark will appear in the box next to the selected entry.

Tip: Press **OPTIONS** (right softkey) > **Enter New Address** or **Contacts** to enter a new phone number or address or to select an entry from your Contacts.

4. When you have selected all the entries you want to add, press **CONTINUE** (left softkey).
5. Enter a group name and press **OK** > **SAVE** (left softkey).

Delete Recent Calls

You can delete individual or all entries in your Recent Calls.

1. From standby mode, press **RECENT CALLS** (left softkey).
2. Highlight an entry you wish to delete and press **OPTIONS** (right softkey) > **Delete**.
 - Select **Delete All** to delete all entries.
3. If you are certain you want to delete one or all entries from Recent Calls, press **DELETE** (left softkey).

Call Timer

Call timer approximates the amount of time you have spent on phone calls.

View Call Timer

1. From standby mode, press **RECENT CALLS** (left softkey).
2. Press **OPTIONS** (right softkey) > **View Call Timer**.
3. View the **Last Call**, **Outgoing Calls**, **Incoming Calls**, **Home Calls**, **Roaming Calls**, **All Calls**, and **Lifetime Calls** durations.

Reset Call Timer

1. From standby mode, press **RECENT CALLS** (left softkey).
2. Press **OPTIONS** (right softkey) > **View Call Timer**.

3. Select the item you want to reset and press **RESET** (right softkey) > **YES** (left softkey).

Note: Lifetime Calls tracks all calls made and received for life of the phone and cannot be reset.

Contacts

Your phone's Contacts help you stay in touch with family, friends, and colleagues by keeping track of all their contact information. This section explains how to use your phone's Contacts.

[View Contacts Entry](#)

[Create a New Contacts Entry](#)

[Edit a Contacts Entry](#)

[Find Contacts Entries](#)

[Use Contacts Information in Other Applications](#)

[Assign Speed Dial Numbers](#)

[Secret Contacts Entries](#)

View Contacts Entry

Access your Contacts entries currently stored in your phone.

[The Contacts List](#)

[Contacts Details](#)

[View Recent Calls From Contacts](#)

The Contacts List

The Contacts list shows the Contacts entries stored in your phone.

1. From standby mode, press **CONTACTS** (right softkey). You will see the Contacts list.
2. Highlight a contacts entry to show the entry's main phone number, or highlight a group entry to show how many members it has.

Contacts Details

You can see details about each of your Contacts by accessing the Contacts list screen.

1. From standby mode, press **CONTACTS** (right softkey).
2. Highlight an entry and press **OK** to show the details.

Tip: Highlight any data field and press **OK** on the details screen. Menu options for that field will appear, if available.

View Recent Calls From Contacts

You can view the call history of a selected Contacts entry from the Contacts list.

1. From standby mode, press **CONTACTS** (right softkey).
2. Highlight an entry and press **OPTIONS** (right softkey) > **Contact History**.

Create a New Contacts Entry

It's easy to add new Contacts entries to your Contacts list.

Create a Contacts Entry

Create a Group Entry

Save a Number Using the Phone Keypad

Create a Contacts Entry

Your phone can store up to 600 Contacts entries. Each entry can contain up to seven phone numbers, and three email addresses, IM addresses, and Web addresses.

1. From standby mode, press **CONTACTS** (right softkey) > **Add New...** > **New Contact**.
2. Enter a name for the new entry and press the navigation key down.
3. Enter the phone number and press **OK**.
4. Highlight a number type for the entry (**Mobile**, **Home**, **Work**, **Pager**, **Fax**, or **Other**) and press **OK**.
5. Press **DONE** (left softkey).

Create a Group Entry

You can create a group by assigning Contacts entries as members and then naming the new group. Each group entry can contain up to 10 members for sending messages.

1. From standby mode, press **CONTACTS** (right softkey) > **Add New...** > **New Group**.
2. Read the message and press **START** (left softkey).
3. Highlight an entry you want to add to a group and press **OK**. A check mark will appear in the box next to the selected entry.
 - If the entry has more than one number, select a number or numbers and press **OK**. Each selected number will be added as a separate entry to the group.

Tip: Press **OPTIONS** (right softkey) > **Enter New Address** or **Recent Calls** to enter a new phone number or address or to select an entry from your recent calls.

4. When you have selected all the entries you want to add, press **CONTINUE** (left softkey).
5. Enter a group name and press **OK** > **SAVE** (left softkey).

Save a Number Using the Phone Keypad

You can save a phone number to Contacts directly from the phone keypad.

1. From standby mode, enter a phone number.
2. Press **OPTIONS** (right softkey) > **Save**. (If this is the first time you are saving an entry to Contacts, skip to step 4.)
3. Select **New Entry** or **Existing Entry**.
4. If you chose **New Entry**, select a number type, and then enter the new entry name.

— or —

If you chose **Existing Entry**, select an entry to which you want to save the number, and then highlight a number type and press **OK**.

5. Press **DONE** (left softkey) to save the entry.

Edit a Contacts Entry

Once you've added a Contacts entry, you can add or edit the information in the entry.

[Edit a Contacts Entry](#)

[Delete a Contacts Entry](#)

[Add a Number to a Contacts Entry](#)

[Assign a Ringer to a Contacts Entry](#)

[Assign a Picture to a Contacts Entry](#)


[Add Members to a Group Entry](#)

[Remove Members From a Group Entry](#)

Edit a Contacts Entry

You can edit existing entries in your Contacts.

1. From standby mode, press **CONTACTS** (right softkey).

2. Highlight the entry you want to edit and press **OPTIONS** (right softkey) > **Edit Contact** or **Edit Group**.
3. Highlight the information you wish to edit.
4. Add or edit the information and press .
5. Press **DONE** (left softkey) or **SAVE** (left softkey) to save your changes.



Delete a Contacts Entry

You can delete existing entries from your Contacts.

1. From standby mode, press **CONTACTS** (right softkey).
2. Highlight an entry or a group you want to delete.
3. Press **OPTIONS** (right softkey) > **Delete Contact** or **Delete Group**.
4. Press **DELETE** (left softkey) or **YES** (left softkey).


Add a Number to a Contacts Entry

You can add numbers to existing entries in your Contacts.

1. From standby mode, press **CONTACTS** (right softkey).
2. Highlight the entry you want to add a number to and press **OPTIONS** (right softkey) > **Edit Contact** > **<Add Number>**.
3. Enter the new number and press .
4. Highlight a label for the number and press .
5. Press **DONE** (left softkey) to save the new number.

Assign a Ringer to a Contacts Entry






Assign a ringer to a Contacts entry so that you can identify the caller by the ringer. See [Ringer Settings](#).

1. From standby mode, press **CONTACTS** (right softkey).
2. Highlight an entry and press .
3. Select **Set Ringers** > **Incoming Calls** or **Message**.
4. Select **Change**.

5. Highlight a ringer category, such as **Default Ringer**, **Downloaded**, **Preloaded Ringers**, or **No Ringer** and then press .
6. Highlight a ringer and press .



Assign a Picture to a Contacts Entry

Assign a picture to display each time a certain contact calls you.

1. From standby mode, press **CONTACTS** (right softkey).
2. Highlight an entry and press .
3. Highlight  and press .
4. Select **Choose Photo**.
5. Select a photo category and press .
6. Select an image and press  to assign it.

Add Members to a Group Entry

You can add a group member to an existing group.

1. From standby mode, press **CONTACTS** (right softkey).
2. Highlight the group you want to add members to and press **OPTIONS** (right softkey) > **Edit Group** > **Add More**.
3. Read the message and press **START** (left softkey).
4. Highlight an entry you want to add and press . A check mark will appear in the box next to the selected entry.
 - If the entry has more than one number, select a number or numbers and press . Each selected number will be added as a separate entry to the group.
5. Repeat step 4 to add additional members.
6. Press **CONTINUE** (left softkey) > **SAVE** (left softkey).

Remove Members From a Group Entry

You can remove group members from existing groups.

1. From standby mode, press **CONTACTS** (right softkey).

2. Highlight the group you want to remove members from and press **OPTIONS** (right softkey) > **Edit Group**.
3. Highlight a member and press **OPTIONS** (right softkey) > **Remove from Group** > **YES** (left softkey).
4. Repeat step 3 to remove additional members.
5. Press **SAVE** (left softkey).

Find Contacts Entries

You can easily search the information stored in your Contacts.

Find an Entry From Contacts

Find an Entry Using the Phone Keypad


Find an Entry From Contacts

You can quickly access the stored information in your Contacts.

1. From standby mode, press **CONTACTS** (right softkey).
2. Scroll through all the entries.

— or —

Enter the first few letters of any part of an entry's name. Contacts with matching letters are listed. (The more letters you enter, the more your search narrows.)


3. Highlight an entry and press  to dial the number displayed. (Press the navigation key left or right to display other listed numbers.)

— or —

Highlight an entry and press  to display the details.

Find an Entry Using the Phone Keypad

You can search Contacts entries for the numbers that contain a specific string of numbers.

1. Enter four or more digits of the number in standby mode. (The more numbers you enter, the more specific the search becomes.)
2. All Contacts entries matching the entered numbers will be displayed.
3. Highlight an entry and press  to dial the number.



— or —

Highlight an entry and press  to display further options available.

Use Contacts Information in Other Applications

You can use saved Contacts information in other applications.

To copy information into a message:

1. From standby mode, press **CONTACTS** (right softkey).
2. Highlight an entry and press .
3. Highlight the information you want to copy, such as phone numbers, email addresses, or URLs, and press .
4. Select **Share > Message**.

After you select one or more recipients, the text entry screen for the type of message specified will open, and the selected text will appear in the body of the message.

Note: For more information about message, see [Messages](#).



Assign Speed Dial Numbers

Your phone can store up to 98 phone numbers in speed dial locations. (See [Call Using a Speed Dial Number](#).)

1. Add a number to a new or to an existing Contacts entry. See [Add a Number to a Contacts Entry](#), if the number is not in your Contacts.

— or —

From standby mode, press **CONTACTS** (right softkey), highlight an entry and press .

2. Highlight the number and press **OPTIONS** (right softkey) > **Set Speed Dial**.
3. Highlight an available speed dial location and press .
4. Press  to return to the contact details screen.

Tip: To replace a current assignment, select a location and press **REPLACE** (left softkey).

To check speed dial assignments:

1. From standby mode, press **CONTACTS** (right softkey).
2. Press **OPTIONS** (right softkey) > **Settings > Speed Numbers**.

Secret Contacts Entries

When you make an entry secret and hide it, that entry is not displayed in your Contacts. In Recent Calls, a telephone number is displayed but the Contacts entry's name is not.

To make an entry secret:

1. From standby mode, press **CONTACTS** (right softkey).
2. Highlight an entry and press **OPTIONS** (right softkey) > **Set as Secret**.
3. Select **On**.

To hide or show secret entries:

1. From standby mode, press **CONTACTS** (right softkey).
2. Press **OPTIONS** (right softkey) > **Settings** > **Hide Secret** or **Show Secret**.
3. Enter the four-digit lock code and press **CONTINUE** (left softkey).

Tip: If you can't recall your lock code, try using the last four digits of your wireless phone number.

Messages

The Messages menu allows you to stay connected 24 hours a day anywhere on the network. With your phone, you can use two types of messages, text messages (SMS) and multimedia messages (MMS). With text messages, you can send and receive instant text messages between your phone and another messaging-ready phone. Multimedia messages consist of both text and multimedia files, such as pictures or voice recordings.

[Compose Messages](#)

[Access Messages](#)

[Threaded Messages](#)

[Messages Settings](#)

[Simple Data Exchange](#)

Compose Messages

Use your phone to send text messages.

1. Press **OK** > **Messages** > **Send Message**.
2. Select a recipient from the list or from the following options:
 - **Go to Contacts** to select a recipient from your Contacts. (Qualifying Contacts entries must contain a phone number.)
 - **MULTIPLE** (left softkey) to select multiple recipients. Press **CONTINUE** (left softkey) when you have finished selecting and entering recipients. (You may include up to 10 recipients per message.)
 - **NEW ADDRESS** (right softkey) to enter a recipient's phone number directly. Press **CONTINUE** (left softkey) to proceed.
3. Compose a message.
 - Press **OPTIONS** (right softkey) to select additional options.
4. Select **<Add Attachment>** and select a category of files you would like to attach (**Picture** or **Audio**).
5. Select a location where your file is stored. (You can also choose to take a new picture or to record a new audio.)
6. Select files you would like to attach.

7. Review your message and press **SEND** (left softkey).

Access Messages

Read and reply to the messages you have received.

To read a message:

- When you receive a message, your phone will display a notification message. Use your navigation key or select **View**.

To reply to a message:

1. While the message is displayed, press **REPLY** (left softkey).
2. Compose a reply and press **SEND** (left softkey).

Threaded Messages


Threaded messages lets you follow a chain of messages to and from a particular contact.

To display the thread list:

- From standby mode, press  > **Messages** > **Messages**.

You will see a thread list. Each thread has an entry's name (if saved in Contacts) or a phone number. You will also see the number of unread messages, if any, for each thread.

View Messages

Highlight a thread and press  to display the messages sent to and received from a particular contact, in reverse chronological order. Failed, pending, and draft messages are also listed.

Highlight a message to see details for that message.

- **Me** - Message you sent.
- **Me (Failed)** - Message you did not send successfully.
- **Me (Pending)** - Message you have not sent yet because your phone has no network connection. The message will be sent automatically when your phone reconnects to the network.
- **Me (Draft)** - Message you saved as a draft. Only one draft can be saved in each thread, and that draft appears at the top of the thread.


Message Details

Highlight a message and press  to display the message details and view the entire message.

You can select certain information from a message and automatically save it or use it in a related application. See [Simple Data Exchange](#).

Threaded Messages Options

When you are viewing a messages thread list, a message thread, or a message details screen, you can choose from among the following options. (Options will vary according to screen.)

- ▶ Press  or **SPEAKER** to make a call.
- ▶ Press **SEND MESSAGE** (left softkey) to send a message to the entry.
- ▶ Press **REPLY** (left softkey) to reply to a message.
- ▶ Press **SEND** (left softkey) to send a draft message.
- ▶ Press **RESEND** (left softkey) to resend a failed message.
- ▶ Select a message, press **OPTIONS** (right softkey) and select an option:
 - **Forward** to forward the selected message.
 - **Lock** to lock the selected message.
 - **Unlock** to unlock the selected message.
 - **Unlock All** to unlock all messages.

Note: Messages are automatically deleted starting with the oldest. To save messages, lock them.

- **Delete** to delete the selected message.
- **Delete All** to delete all messages.
- **Call** to dial the phone number appearing in the selected message.
- **Launch** to open the URL appearing in the selected message.
- **Save Number** to save the phone number appearing in the selected message.
- **Save Email** to save the email address appearing in the selected message.
- **Settings** to display the Messages Settings menu.

Messages Settings

Your phone's advanced message capabilities let you send and receive different kinds of messages without placing a voice call. Messages settings allow you to create a signature with each sent message and your own preset messages.

Set Reset Envelope

Reset Envelope will clear the envelope icon on the display.

1. Press **OK** > **Messages** > **OPTIONS** (right softkey) > **Reset Envelope**.
2. Press **YES** (left softkey).

Set a Callback Number

With this feature, you can specify the callback number which your recipients see when you send messages.

1. Press **OK** > **Messages** > **OPTIONS** (right softkey) > **Callback Number**.
2. Select **None**, **My Phone Number**, or **Other**.
 - If you select **Other**, enter a callback number and press **OK**.

Add a Customized Signature

Add a customized signature to each message you send.

1. Press **OK** > **Messages** > **OPTIONS** (right softkey) > **Signature**.
2. Select **On**. (If you do not wish to attach a signature to your outgoing messages, select **Off**.)
3. Enter a signature and press **OK**.

Manage Preset Messages

Your phone is loaded with preset messages to help make sending messages easier. Customize or delete these messages, such as "What's up?," "Where are you?," and "Check this out!" to suit your needs, or add your own messages to the list.

To edit or delete a preset message:

1. Press **OK** > **Messages** > **OPTIONS** (right softkey) > **Preset Messages**. (The list of preset messages will be displayed.)
2. To edit or delete a message, highlight it and press **OPTIONS** (right softkey).
3. Select **Edit**, edit the message, and press **OK**.

— or —

Select **Delete** > **YES** (left softkey) to delete the message. (You can also reset all messages by selecting **Reset all messages** > **YES** [left softkey].)

To change the language of the preset message:

1. Press **OK** > **Messages** > **OPTIONS** (right softkey) > **Preset Messages**.
2. Press **OPTIONS** (right softkey) > **Select Language**.
3. Select **English** or **Français**.

Simple Data Exchange

This feature makes it easy to select certain information in a message or calendar event and automatically save it or use it in a related application.

Simple Data Exchange works with these types of information:

- Email addresses
- Phone numbers
- Web addresses (URLs)

Email Address Options


- ▶ Highlight an email address, press **OK**, and then select an option:
 - **Share** to select **Message**. The messaging application will open and the email address will appear in the message body.
 - **Save to Contacts** to save the email address in Contacts.
 - **Contact Details** to display the Contacts entry if the email address is already saved in Contacts.

Phone Number Options

- ▶ Highlight a phone number, press **OK**, and then select an option:
 - **Call** to call the phone number.
 - **Prepend** to prepend a number to the phone number.
 - **Send Message** to send a message to the phone number. The messaging application will open and the phone number will appear as the message's recipient.
 - **Share** to select **Message**. The messaging application will open and the phone number will appear in the message body.

- **Save to Contacts** to save the phone number in Contacts.
- **Contact Details** to display the Contacts entry if the phone number is already saved in Contacts.

Web Address (URL) Options

- ▶ Highlight a Web address (URL), press , and select an option:
 - **Browse** to open the browser to the Web page.
 - **Share** to select **Message**. The messaging application will open and the Web address will appear in the message body.
 - **Save to Contacts** to save the Web address in Contacts.

Calendar

Use Calendar to create and manage events, meeting, and appointments. Your Calendar helps organize your time and reminds you of important events.

[Add an Event to the Calendar](#)

[Add a To Do List Item to the Calendar](#)

[Calendar Alerts](#)

[View Events](#)

[Delete Events](#)

Add an Event to the Calendar

Your Calendar helps organize your time and reminds you of up to 100 important events.

1. Press **OK** > **Calendar**.
2. Highlight a day to which you would like to add an event and press **OPTIONS** (right softkey) > **Add Schedule**.
3. Enter a description and press **OK**.
4. Select a category for the event (Appointment, Meeting, etc.) by highlighting the category field and pressing **OK**.
5. Select a priority for the event by highlighting the priority field and pressing **OK**.
6. Select a start and end time for the event by highlighting the start and end time fields and pressing **OK**.
7. Enter a location for the event by highlighting the location field and pressing **OK** > **EDIT** (left softkey). Press **OK** when you have finished.
8. Select a ringer type for the alarm by highlighting the ringer field and pressing **OK**.
9. Select an alarm time by highlighting the alarm time field and pressing **OK**.
10. Select a repeat status for the alarm by highlighting the repeat field and pressing **OK**.

- If you chose **Specific Period**, set a start and end date for the repeat status and press **OK** (left softkey).
- If you chose **Weekly**, select the check box for each day of the week you wish to set and press **DONE** (left softkey).

11. Press **SAVE** (left softkey).







Tip: To change the calendar display views, press the left softkey (**MONTH** or **WEEK**) repeatedly to toggle between monthly and weekly views.

Tip: On the weekly view, press the navigation key up or down to display the previous week or the next week, respectively.

Tip: Press **OPTIONS** (right softkey) > **Settings** > **Holiday/Weekday** to enter holidays and weekdays.

Add a To Do List Item to the Calendar

Your phone can store and manage up to 40 To Do list items.

1. Press  > **Calendar**.
2. Highlight a day to which you would like to add a To Do list item and press **OPTIONS** (right softkey).
3. Press the navigation key right and select **Add To Do**.
4. Enter a description and press .
5. Select a category for the item by highlighting the category field and pressing .
6. Select a priority for the item by highlighting the priority field and pressing .
7. Select a time and date for the item by highlighting the time and date field and pressing .
8. Select a status for the item by highlighting the status field and pressing . When you add an item, set it to **Needs Action**.
9. Press **SAVE** (left softkey).

Calendar Alerts

If you have an event on the Calendar, your phone alerts you with a ringing or vibrating alarm and displays a summary of the event.

To respond to the alarm, select an available onscreen menu or press the appropriate softkey:



- ▶ Press **SNOOZE** (left softkey) or select **Snooze** to stop the alarm and start snooze mode (if applicable).
- ▶ Press **DISMISS** (right softkey) to clear the alarm (if applicable).
- ▶ Select **View** to display the event detail screen.

Tip: To change the alarm settings, from the main menu select **Calendar** > **OPTIONS** (right softkey) > **Settings** > **Alarm** to set the snooze options.

View Events


Display the scheduled events on your Calendar.

Tip: Days with scheduled events are indicated by small colored rectangles just below the date. A rectangle's color depends on the repeat status for an event.

1. Press  > **Calendar**.
2. Highlight the day for which you would like to view events and press . The day's event list is displayed.



— or —

Press **OPTIONS** (right softkey) > **Schedule List** or **To Do List**.

3. Highlight an event and press . The event's details are displayed. You can edit the event on this screen.


Delete Events

It's easy to delete scheduled events from your Calendar.

1. Press  > **Calendar**.
2. Highlight the day from which you would like to delete an event and press .

— or —

Press **OPTIONS** (right softkey) > **Schedule List** or **To Do List**.

3. Highlight an event and press **OPTIONS** (right softkey) > **Delete**.
4. Highlight an option and press .
 - **This** to delete the highlighted event.
 - **Select** to delete multiple events.

- **All on This List** to delete all events on the list.
- **All Completed Events** to delete completed To Do List items.

5. Press **YES** (left softkey).

To delete old events or all events:

- ▶ Press **OK** > **Calendar** > **OPTIONS** (right softkey) > **Delete Memory** > **Delete Old** (or **Delete All**) > **YES** (left softkey).

Tools

Learn how to use many of your phone's productivity-enhancing features.

Alarm

Voice Services

Calculator












World Clock


Countdown Timer

Stopwatch

Alarm

Your phone comes with a built-in alarm that has multiple alarm capabilities.

1. Press  > **Tools** > **Alarm**.
2. Highlight an alarm number and press .
3. Turn the alarm on or off by highlighting the alarm field and pressing 
 - Highlight **On** or **Off** and press .
4. Enter a description for the alarm by highlighting the description field and pressing .
5. Select a time for the alarm by highlighting the time field and pressing .
6. Select a repeat status for the alarm by highlighting the repeat field and pressing .
7. Select a ringer option for the alarm by highlighting the ringer field and pressing .
8. Select a volume level for the alarm by highlighting the volume field and pressing .
9. Select a ringer length for the alarm by highlighting the ringer length field and pressing .
10. Select a snooze interval for the alarm by highlighting the snooze interval field and pressing .

11. Select the number of times the snooze should repeat by highlighting the snooze time field and pressing .
12. Press **SAVE** (left softkey).

Tip: Press **ON** or **OFF** (left softkey) to toggle the alarm on and off.

Voice Services

Your phone's voice services let you place calls using your voice, store voice reminders, and record memos right on your phone. This section includes easy-to-follow instructions for using voice-activated features and managing voice memos.

Automatic Speech Recognition (ASR)

Manage Voice Memos

Automatic Speech Recognition (ASR)

You can use your phone's built-in automatic speech recognition (ASR) software to dial a phone number or to launch phone functions. All you have to do is to talk into the phone, and ASR will recognize your voice and complete tasks by itself.

Activate ASR

- From standby mode, press and hold  or **SPEAKER**.

The phone prompts you to say the name of the command you want to use. To complete your task, simply follow the voice prompts.


Available ASR commands include:

- **Call** <Name or #> to call an entry in your Contacts list or a spoken phone number. See [Make a Voice Call Using ASR](#) for details.
- **Send Message** <Name or #> to send a message to an entry in your Contacts list or to a spoken phone number. See [Send a Message Using ASR](#) for details.
- **Lookup** <Name> to display the detail screen of an entry in your Contacts list. See [Display a Contacts Entry's Information Using ASR](#) for details.
- **Go To** <Menu> to jump directly to menu items or applications. See [Open Menus Using ASR](#) for details.
- **Check** <Item> to check your phone's status. See [Check Phone Status Using ASR](#) for details.

Tip: Use ASR in a quiet environment so it can accurately recognize your commands.

Tip: During ASR operation, press **TUTORIAL** (left softkey) or **HELP** (left/right softkey) to get instructions for using the software.


Make a Voice Call Using ASR

1. Press and hold  or **SPEAKER**.
2. When you hear “Say a command,” say “**Call.**”
3. When you hear “Say the name or number,” say a name or a phone number.
4. When you hear “Which location?,” say a number type (for example, “Mobile”).


Tip: You can skip steps 3 and 4 by saying a name and location after “Call” without pausing (for example, “**Call John Jones mobile**”).

Note: If ASR does not recognize the name or number, it will find the most likely matches and display a list of up to three names or numbers. You will hear “Did you say, ‘Call...?’” followed by the name or number. You can confirm by saying “Yes.” Say “No” to change the selection.

Send a Message Using ASR


1. Press and hold  or **SPEAKER**.
2. When you hear “Say a command,” say “**Send Message.**”
3. When you hear “Say the name or number,” say a name or a phone number.
4. When you hear “Which location?,” say a number type (for example, “Mobile”). The phone displays the text entry screen. See [Messages](#) for how to compose a message.

Display a Contacts Entry's Information Using ASR

1. Press and hold  or **SPEAKER**.
2. When you hear “Say a command,” say “**Lookup.**”
3. When you hear “Say the name,” say a Contacts entry’s name. The phone displays the detail screen for that Contacts entry.

Open Menus Using ASR

You can jump directly to many menu items or applications by saying “Go to” followed by a menu option.

1. Press and hold  or **SPEAKER**.
2. When you hear “Say a command,” say “**Go To.**”



3. When you hear “Which shortcut?,” say an application name (for example, “Messages”).
4. The phone opens the selected menu.

Tip: Say “**More Options**” to display additional application names.

Check Phone Status Using ASR




You can use ASR to obtain information about your phone:

- **Status** (all of the following except My Phone Number)
- **Time**
- **Signal Strength**
- **Network**
- **Battery**
- **My Phone Number**

1. Press and hold  or .
2. When you hear “Say a command,” say “**Check.**”
3. When you hear “Which status item?,” say a command.

ASR Settings

To change ASR confirmation:

1. Press and hold  or .
2. Press **SETTINGS** (right softkey) > **Confirmation**.
3. Highlight an option and press - **Automatic** to ask for confirmation only when the system is not sure what you said.
- **Always Confirm** to always ask for confirmation.
- **Never Confirm** to never ask for confirmation.

To adapt the system to your voice:


1. Press and hold  or .
2. Press **SETTINGS** (right softkey) > **Adaptation** > **Adapt Voice**.

3. Press **START** (left softkey) and repeat each word, phrase, or telephone number you hear.


To reset the adaptation:

1. Press and hold  or **SPEAKER**.
2. Press **SETTINGS** (right softkey) > **Adaptation** > **Reset Voice** > **YES** (left softkey).


To change the ASR mode:

1. Press and hold  or **SPEAKER**.
2. Press **SETTINGS** (right softkey) > **Audio Modes**.
3. Highlight an option and press **OK**.
 - **Expert Mode** to sound a beep only.
 - **Prompt Mode** to prompt for required information.
 - **Readout Mode** to prompt for required information and to read the text displayed on the main screen.

To change the ASR dialing region:

1. Press and hold  or **SPEAKER**.
2. Press **SETTINGS** (right softkey) > **Dialing Region**.
3. Highlight an option and press **OK**.
 - **North America** to recognize only numbers valid in North America.
 - **Other** to recognize any number regardless of location.

To display the ASR software version:

1. Press and hold  or **SPEAKER**.
2. Press **SETTINGS** (right softkey) > **About**.




Manage Voice Memos

Use your phone's Voice Memo to record brief memos to remind you of important events, phone numbers, or grocery list items and to record call memos of the other party's voice during a phone call.

Note: You can store up to 2000 memos on your phone. Maximum recording time depends on the available memory space on your phone.

Record Voice Memos

To record an audio memo:

1. Press  > **Tools** > **Voice Services** > **Voice Memo** > **Record**.
2. Start recording after the beep.
3. To stop recording, press , , or **STOP** (right softkey).

To record the other party's voice during a phone call:



1. During a call, press **OPTIONS** (right softkey) > **Voice Memo**.
2. Start recording after the beep.

Note: Only the other party's voice is recorded during this process.

3. To stop recording, press  or **STOP** (left softkey).

Play Voice Memos


To play one or all memos:

1. Press  > **Tools** > **Voice Services** > **Voice Memo** > **List**.
2. Highlight the memo you want to play and press .

— or —


Press **OPTIONS** (right softkey) > **Play** > **All** to play all memos continuously.

To play multiple memos:

1. Press  > **Tools** > **Voice Services** > **Voice Memo** > **List**.
2. Press **OPTIONS** (right softkey) > **Play** > **Multiple** and select memos you want to play.
3. Press **PLAY** (left softkey).

Voice Memo Options

Your phone offers several options for managing voice memos you have recorded.

1. Press  > **Tools** > **Voice Services** > **Voice Memo** > **List**.
2. Highlight a memo and press **OPTIONS** (right softkey) to display available voice memo options:

- **Play** to play selected memos or all memos. Select from **This**, **Multiple**, or **All**.
- **Speaker On** or **Speaker Off** to activate or deactivate the speakerphone mode.
- **Edit Title** to edit the title of a memo.
- **Properties** to display information about a memo.
- **Type Filter** to filter only audio memos, only call memos, or to display all memos.
- **Sort by** to sort memos by time recorded, name, or file size.
- **Go to Time** to set the point from which the memo starts playing.
- **Send Media** to send a memo by attaching it to a message (if applicable).
- **Delete** to delete either selected memos or all memos. Select from **This**, **Multiple**, or **All**.

Calculator

Your phone comes with a built-in calculator.

1. Press **OK** > **Tools** > **Calculator**.
2. Enter numbers using your keypad.
 - Press the appropriate key for an arithmetic option (+ − × ÷).
 - Press the left softkey to enter a decimal point.
 - Press **CLEAR** (right softkey) to clear all numbers.
3. Press **OK** for the total.

World Clock

You can view the local time in various cities around the world.

To view the time in different locations:

1. Press **OK** > **Tools** > **World Clock**.
2. Press the navigation key left or right to scroll through different time zones.

Note: Press **OPTIONS** (right softkey) > **Standard** or **Summer** to change between daylight saving time and standard time.

Countdown Timer

This feature allows you to use your phone as a countdown timer to alert you when a specified period of time has elapsed. You can set up to five timers.

1. Press **OK** > **Tools** > **Countdown**.
2. Highlight a countdown timer number and press **OK**.
3. Highlight a setting and press **OK**.
 - **Time** to enter the length of the countdown.
 - **Alarm** to set the countdown alarm to on or off.
4. Press **SAVE** (left softkey).

Tip: Press **ON** or **OFF** (left softkey) to toggle the countdown alarm on and off.

Stopwatch

You can record split times or lap times with the built-in stopwatch.

1. Press **OK** > **Tools** > **Stopwatch**.
2. Press **MODE** (left softkey) to select split timing or lap timing.
3. Press **START** (right softkey) to start the stopwatch.
4. Press **SPLIT** or **LAP** (left softkey) to record the time.
5. Press **STOP** (right softkey) to stop timing.
6. Press **RESET** (left softkey) to reset the stopwatch to zero.

Bluetooth

Bluetooth® is a short-range communications technology that allows you to connect wirelessly to a number of Bluetooth devices, such as headsets and hands-free car kits, and Bluetooth-enabled handhelds, computers, printers, and wireless phones. The Bluetooth communication range is usually approximately 30 feet.

[Turn Bluetooth On and Off](#)

[Make Your Phone Discoverable](#)

[Bluetooth Menu](#)

[Pair Bluetooth Devices](#)

[View the Trusted Devices List](#)

[Send Items via Bluetooth](#)

Turn Bluetooth On and Off

By default, your phone's Bluetooth feature is turned off. Turning Bluetooth on enables your phone's Bluetooth functions.

1. Press **OK** > **Bluetooth** > **On/Off**.
2. Press **ON** (left softkey) to enable Bluetooth. Press **OFF** (left softkey) to disable Bluetooth.

Note: Turn off Bluetooth when not in use to conserve battery power, or in places where using a wireless device is prohibited, such as aboard an aircraft and in hospitals.




Make Your Phone Discoverable

To make your phone discoverable (allowing other Bluetooth devices to detect it), you must set your phone's visibility to other than **Hidden**.

1. Press **OK** > **Bluetooth** > **Visibility**.
2. Select **Visible for 3 min** or **Always visible**. If you select **Always visible**, your phone will be discoverable by all in-range Bluetooth devices until you change the setting. If you select **Visible for 3 min**, your phone will return to hidden mode after three minutes.

Bluetooth Status Indicators

The following icons show your Bluetooth connection status at a glance:

Icon	Description
	Your phone's Bluetooth feature is turned on.
	Your phone is visible to other Bluetooth devices.
	Your phone is connected to a Bluetooth device.


The above icons will blink while your phone is communicating with a Bluetooth device.

Bluetooth Menu

The **Bluetooth** menu allows you to set up many of the characteristics of your phone's Bluetooth feature, including:

- Setting your phone's visibility (or "discoverability") for other Bluetooth devices.
- Adding a new Bluetooth device to your phone.
- Displaying your Bluetooth trusted devices list.
- Displaying your phone's Bluetooth information.

To access the Bluetooth menu:

- ▶ Press  > **Bluetooth** to select from following options:
 - Select **On/Off** to enable or disable Bluetooth.
 - Select **Visibility** > **Hidden**, **Visible for 3 min**, or **Always visible** to set your Bluetooth visibility.
 - Select **Add New** to add a new Bluetooth device.
 - Select **Trusted Devices** to display a list of trusted Bluetooth devices.
 - Select **My Bluetooth Info** to display your phone's Bluetooth name, address, class, and supported profiles.

Pair Bluetooth Devices

The Bluetooth pairing process allows you to establish trusted connections between your phone and another Bluetooth device. When devices are paired, a passkey (PIN) is shared between

devices, allowing for fast, secure connections while bypassing the discovery and authentication process.

1. Press **OK** > **Bluetooth** > **Add New**.
2. Select the device you wish to pair with and press **OK**.
3. If prompted, accept the connection on the receiving device, and enter the same passcode on both your phone and the other device, or confirm the auto-generated passcode, and then press **OK**.
4. (Optional) Edit the device name and press **SAVE** (left softkey).

Note: Due to different specifications and features of other Bluetooth compatible devices, display and operations may be different, and functions such as transfer or exchange may not be possible with all Bluetooth compatible devices.

View the Trusted Devices List

This list displays a list of devices which are paired with your phone and set as trusted devices.

- Press **OK** > **Bluetooth** > **Trusted Devices**.

Trusted Devices List Menu

Once you have created trusted devices, several options are available from the Trusted Devices list.

Left Softkey Menus

1. Press **OK** > **Bluetooth** > **Trusted Devices**.
2. Highlight a device and press the available left softkey options:
 - **CONNECT...** to connect to the selected Bluetooth device, if not connected (for headsets, hands-free and other devices, excluding computers, PDAs, phones, or printers).
 - **TRANSFER...** to send data saved on your phone to the selected Bluetooth device (for computers, PDAs, or phones). See [Send Items via Bluetooth](#).

Options Menu

1. Press **OK** > **Bluetooth** > **Trusted Devices**.
2. Highlight a device and press **OPTIONS** (right softkey) to display the following options:
 - **Add New** to add a new Bluetooth device.

- **Delete** to delete the selected device from the list.
- **Delete All** to delete all devices from the list.
- **Auto-Accept** to configure your phone's accessibility to other Bluetooth devices.
- **View/Edit Info** to view or edit the information of the selected device.
- **Help** to display the Trusted Devices list help.

Send Items via Bluetooth

Depending on your paired devices' settings and capabilities, you may be able to send Contacts information or other items using a Bluetooth connection.

1. Press **OK** > **Bluetooth** > **Trusted Devices**.
2. Select the device from the Trusted Devices list and press **TRANSFER...** (left softkey).
3. Select an item (**Send Contacts**, **Send Name Card** or **Exchange Name Cards**) and press **OK**.
4. Follow the onscreen instructions to select items to send.
5. Read the message and press **SEND** (left softkey).

Camera

You can use the camera to take and share pictures. Your phone comes with a 2.0 megapixel camera.

[Take Pictures](#)

[Store Pictures](#)

[Send Pictures](#)

Take Pictures

Taking pictures with your phone's built-in camera is as simple as choosing a subject, aiming the lens, and pressing a button.

[Take a Picture](#)

[Assign Pictures](#)

[Camera Mode Options](#)


[Camera Settings](#)

[Camera Icons](#)





[Use Other Settings Menu](#)

Take a Picture

It's easy to take a picture.

1. Press  > **Camera** to activate camera mode. Additional camera options are available. See [Camera Mode Options](#) for more information.

Shortcut: To activate camera mode, you can also press and hold the camera key (.

2. Using the phone's main screen as a viewfinder, aim the camera lens at your subject.
3. Press , , or **CAPTURE** (left softkey) until the shutter sounds. The picture will automatically be saved in the selected storage area. See [Store Pictures](#).
 - To return to camera mode to take another picture, press **CAMERA** (left softkey), , or .
4. Press **OPTIONS** (right softkey) for more options.
 - **Send Message** to send your picture in a message. See [Send Pictures](#).

- **Assign** to assign a picture as a picture ID or as a wallpaper. See [Assign Pictures](#).
- **Delete** to delete the picture you just took.
- **Review Media** to go to the My Photos folder to review your saved pictures.
- **Details/Edit** to edit your picture or display details relating to your pictures.

Assign Pictures

Assign a picture as a wallpaper or as a picture ID.

1. Take a picture. See steps 1-3 on [Take a Picture](#).
2. With the picture displayed, press **OPTIONS** (right softkey) > **Assign**, and select an option.
 - **Picture ID** to assign the picture to a Contacts entry as well as to unsaved phone numbers, or to private and unknown phone numbers. See [Select a Picture ID](#).
 - **Wallpaper** to assign the picture as a wallpaper.

Tip: You can also assign pictures from the My Photos menu. See [My Photos Folder Options](#).

Camera Mode Options




Various options are available from camera mode.

Press **OPTIONS** (right softkey) in camera mode to display additional camera options:

- **Picture Mode** to select a picture mode from **Normal**, **Beach/Snow**, **Scenery**, **Mirror Image**, or **Night/Dark**.
- **Zoom** to zoom in on a subject. See [Zoom](#).
- **Self-Timer** to activate the camera's timer. See [Self-timer](#).
- **Fun Tools** to select an option from the following:
 - **Multiple Shots** to take multiple shots. See [Multiple Shots](#).
 - **Fun Frames** to select your favorite fun picture frame to decorate your picture (displayed only when the resolution setting is 0.3M [480x640] or 0.1M [240x320]).
 - **Color Tone** to select a wide variety of color tones for the picture.
- **Image Controls** to adjust settings for **Brightness**, **White Balance**, **Sharpness**, or **Contrast**.
- **CameraSettings** to adjust **Resolution**, **Quality**, and other settings. See [Camera Settings](#).

- **Review Media** to go to the My Photos folder to review your saved pictures.
- **Key Guidance** to show keypad shortcuts in camera mode.
- **User Settings** to provide convenient access to your favorite settings.


Self-timer

1. From camera mode, press **OPTIONS** (right softkey) > **Self-Timer**.
2. Highlight a delay time (**5 Seconds** or **10 Seconds**) and press .
3. Press , , or **START** (left softkey) when you are ready to start the timer. (A countdown is displayed in the middle of the screen and your phone will beep during the countdown.)
4. Get ready for the picture. (When the timer is down to three seconds, the tone of the beep will change.)

To cancel the self-timer after it has started:





- Press **CANCEL** (right softkey) or .

Multiple Shots

This feature allows you to take three, six, or nine shots in a continuous sequence. When you take multiple shots, the  icon will be displayed on the upper left side of the screen.

1. From camera mode, press **OPTIONS** (right softkey) > **Fun Tools** > **Multiple Shots**.

Note: When taking multiple shots, the resolution is temporarily set to **0.1M (240x320)**.

2. Highlight an option (**3 Shots**, **6 Shots**, or **9 Shots**) and press .
 - Select **Off** to deactivate the multiple shots option.
3. Highlight the duration of the interval between shots (**Normal** or **Fast**) and press .
4. Press , , or **CAPTURE** (left softkey) to take the pictures. (The screen will display up to nine thumbnail pictures.)

Zoom


This feature allows you to zoom in on an object when you take a picture. You can adjust the zoom from 1x to 12x.

1. From camera mode, press the navigation key right to zoom in or left to zoom out.












2. Press , , or **CAPTURE** (left softkey) to take a picture.

Camera Settings

You can customize the camera settings.



1. From camera mode, press **OPTIONS** (right softkey) > **CameraSettings**.
2. Highlight an option and press :
 - **Resolution** to select a picture's file size from **2.0M (1200x1600)**, **1.3M (960x1280)**, **0.3M (480x640)**, or **0.1M (240x320)**.
 - **Quality** to select the picture quality setting (**Fine**, **Normal**, or **Economy**).
 - **Shutter Sound** to select a shutter sound (**Default**, **"Say Cheese,"** or **"Ready"**).
 - **Status Bar** to display or hide status indicators and softkeys. These can be revealed or hidden by pressing the navigation key up or down.

Camera Icons

Function		Icon	Description
Picture Mode	Beach/Snow		Use this setting in bright light.
	Scenery		Use this setting for scenery at a distance.
	Mirror Image		Use this setting to take a mirror image.
	Night/Dark		Use this setting in low light.
Resolution	2.0M		For 2.0 megapixel picture resolution.
	1.3M		For 1.3 megapixel picture resolution.
	0.3M		For 0.3 megapixel picture resolution.
	0.1M		For 0.1 megapixel picture resolution.
Self-Timer	5 Seconds		Numeric countdown will appear when the self-timer has been started.
	10 Seconds		
Multiple Shots			Use this setting for multiple shots.

Use Other Settings Menu

The Other Settings menu allows you to set up many of the settings of your phone's picture's function.

1. Press  > **Other Settings**.
 2. Select one of the following options and press .
- **Location** to select whether to include the location information.
 - **Status Bar** to select whether to display the information bar for the pictures.
 - **Slideshow Interval** to set the slideshow interval time.
 - **Help** to view the Photos instruction page.

Store Pictures

Your phone's picture storage area is called **My Photos**. From the My Photos folder, you can view all the pictures you have stored there, delete files, and access additional options.

[Review Pictures in the My Photos Folder](#)

[My Photos Folder Options](#)

[Review Pictures in the Assigned Media Folder](#)

Review Pictures in the My Photos Folder

To review your stored pictures in the My Photos folder:

- Press  > **My Photos**.

My Photos Folder Options

When you are viewing the My Photos folder, press **SEND MESSAGE** (left softkey) to send your pictures (see [Send Pictures](#)), or **OPTIONS** (right softkey) to display the following options:



- **Select Multiple** to select multiple pictures.
- **Slideshow** to view your pictures in slideshow mode (only available when you save two or more pictures to the folder).
- **Assign** to assign a picture as a picture ID or as a wallpaper.
- **Delete** to delete pictures. Select **This**, **Selected**, or **All**.

Note: Deleting data will free up memory space in your phone to enable you to take more pictures.

- **Details/Edit** to edit or display details relating to your pictures.
 - **Text Caption** to edit the selected picture's caption.
 - **Special Effects** to select from **Fun Frames**, **Color Tone**, **Fun Stamps**, or **Rotate**.
 - **Resize** to resize the selected picture. Select **1.3M (960x1280)**, **0.3M (480x640)**, or **0.1M (240x320)**. (Some options may not be available depending on the size of picture you have.)
 - **Trimming** to crop the selected picture.
 - **Photo Info** to display information such as the picture's caption, time/date, and size.
 - **Full Screen** to display the selected picture in full screen view.

Review Pictures in the Assigned Media Folder


The Assigned Media folder automatically stores copies of pictures assigned as picture IDs or wallpapers on your phone. See [Assign Pictures](#).

1. Press  > **Tools** > **Assigned Media**.
2. Use your navigation key to view and scroll through the pictures. (To switch a picture from thumbnail view to expand view mode, highlight a picture and press .)

Send Pictures

Once you have taken a picture, you can use the message capabilities of your phone to instantly share it with family and friends as an attachment.

To send pictures:

1. Press  > **My Photos**.
2. Select your pictures to send.
 - Press **OPTIONS** (right softkey) > **Select Multiple** to select multiple pictures.
3. Press **SEND MESSAGE** (left softkey) and select the recipient from the list or from the following options:
 - **Go to Contacts** to select a recipient from your Contacts. (Qualifying Contacts entries must contain a phone number.)
 - **MULTIPLE** (left softkey) to select multiple recipients. Press **CONTINUE** (left softkey) when you have finished selecting and entering recipients. (You may include up to 10 recipients per message.)

- **NEW ADDRESS** (right softkey) to enter a recipient's wireless phone number directly. Press **CONTINUE** (left softkey) to proceed.
4. Compose a message.
 5. Confirm the recipients, message, and pictures. (You may also select additional options by pressing the right softkey. Follow the onscreen instructions to add available options.)
 6. Press **SEND** (left softkey) to send the pictures.

Multimedia

The Multimedia menu allows you to take a picture, view images, assign a preloaded items to a phone function, and manage your downloaded ringers, images, etc.

[Photos](#)

[Downloaded Files](#)

[Preloaded Files](#)

Photos

In Photos, you can view and manage all taken or downloaded images stored on your phone. The camera is also accessible within this menu screen. See [Camera](#) for more details on camera.

[View Your Pictures](#)

[Assign Your Pictures](#)

[Delete Your Pictures](#)

View Your Pictures

1. Press **OK** > **Multimedia** > **Photos** > **My Photos**.
2. Use your navigation key to view and scroll through the pictures. (To switch a photo from thumbnail view to expand view mode, highlight a photo and press **OK**.)

Assign Your Pictures

1. Press **OK** > **Multimedia** > **Photos** > **My Photos**.
2. With the pictures displayed, press **OPTIONS** (right softkey) > **Assign**, and select an option.
 - **Picture ID** to assign the picture to a Contacts entry as well as to unsaved phone numbers, or to private and unknown phone numbers. See [Assign a Picture to a Contacts Entry](#).
 - **Wallpaper** to assign the picture as a wallpaper.

Delete Your Pictures

1. Press **OK** > **Multimedia** > **Photos** > **My Photos**.
2. With the pictures displayed, press **OPTIONS** (right softkey) > **Delete** > **This** or **All**.

3. Read the message and press **DELETE** (left softkey).

Downloaded Files

The files you download from the website are stored in your phone's internal storage. You can use the Downloaded menu to view, reopen, or delete what you've downloaded.

[View Downloaded Files](#)

[Erase Downloaded Files](#)

View Downloaded Files

1. Press **OK** > **Multimedia** > **Downloaded**. (You will see a list of your downloaded items.)
2. Select a download category and press **OK**. (You will see your downloads for that category.)
3. Press **OPTIONS** (right softkey) and select your desired option:
 - **Listen** to listen to the audio file.
 - **View** to view the image file.
 - **Assign** to assign the downloaded file to a phone function.
 - **Properties** to display information about a downloaded file.
 - **Delete** to delete the selected downloaded file.
 - **Delete All** to delete all downloaded files.
 - **Sort by** to sort downloaded files by name, size or date in ascending or descending order.
 - **Icon/Size** to switch between icon and file size views.

Erase Downloaded Files

1. Press **OK** > **Multimedia** > **Downloaded**. (You will see a list of your downloaded items.)
2. Select a download category and then select an item you wish to delete.
3. Press **OPTIONS** (right softkey) > **Delete** or **Delete All**.
4. Read the message and press **YES** (left softkey).

Preloaded Files

You can assign the preloaded ringers, wallpaper, screen saver or picture ID to a phone function.

To use the preloaded files:

1. Press **OK** > **Multimedia** > **Preloaded**.
2. Select a category (**Wallpaper**, **Screensaver**, **Picture ID**, or **Ringers**) and any applicable subcategories.
3. Use the navigation key to search through available files. When you find one you want, highlight it and press **OK**.

Web and Data

Your phone's data capabilities let you wirelessly access the Internet. This section addresses your phone's data connections and the built-in Web browser.

[Data Services](#)

[Browser](#)

[Info Portal](#)

Data Services

If your plan includes data services, you are ready to start enjoying the advantages of data services. This section will help you learn the basics of using your data services, including launching a data connection and navigating the Web with your phone.

[Launch a Web Connection](#)

[Data Connection Status and Indicators](#)

Launch a Web Connection




Launching a Web connection is as simple as opening the browser on your phone.

► Press  > **Browser**. (Your data connection starts and you see the home page.)

Tip: To change the default launch page to the last page you viewed, press **Options** (right softkey) and select **Browser settings > Startup page > Use the last page I visited > Confirm** (left softkey).

Data Connection Status and Indicators

Your phone displays the current status of your data connection through indicators at the top of the screen. The following symbols are used:

Icon	Description
	Your phone is within the data network service area. This icon is animated while your phone is transferring data (for example, when you are opening a Web page).
	Your phone is within the data network service area, but you are not transferring data (for example, when you are viewing a Web page that has already been opened), or you are signed out or disconnected from the data network.
	Your phone is outside of the data network service area.

Browser

Your phone's Web browser gives you access to websites on the go, using data connections.

[Learn to Navigate the Web](#)

[Browser Menu](#)

Learn to Navigate the Web


Navigating through menus and websites during a data session is easy once you've learned a few basics.

Softkeys

During a data session, the bottom line of your phone's display screen contains one or more softkeys. These keys are shortcut controls for navigating around the Web, and they correspond to the softkeys directly below the phone's display screen.

Tip: Depending on which websites you visit, the labels on the softkeys may change to indicate their function.

To use softkeys:

- ▶ Press a softkey. (If an additional pop-up menu is displayed when you press the softkey, select the menu items using your keypad [if they're numbered], or by highlighting the option and pressing 

Scrolling

As with other parts of your phone's menu, you'll have to scroll up and down to see everything on some websites.


To scroll line by line through websites:

- ▶ Press the navigation key up or down.

Selecting

Once you've learned how to use softkeys and scroll, you can start navigating the Web.

To select onscreen items:

- ▶ Use the navigation key to highlight an item and press 

Tip: If the items on a page are numbered, you can use your keypad (number keys) to select an item.

Links, which are displayed as underlined text, allow you to jump to Web pages, select special functions, or even place phone calls.

To select links:

- ▶ Highlight the link and press the appropriate softkey.

Go Back

To go back one page:

- ▶ Press  on your phone.

Tip: You can also use  for deleting text (like a BACKSPACE key) when you are entering text.

Browser Menu


Although the home page offers a broad and convenient array of sites and services for you to browse, not all sites are represented, and certain functions, such as going directly to specific websites, are not available. For these and other functions, you will need to use the browser menu. The browser menu offers additional options to expand your use of the Web on your phone.

Open the Browser Menu

You may open the browser menu anytime you have an active data session, from any page you are viewing.

- ▶ From any open Web page, press **Navigation** (left softkey). Use the navigation window for the following operations.


To open a specific page:

- ▶ Highlight the text input field on the top, enter a URL and press .

To open a new window:

- ▶ Highlight **Open a new page** and press .

To switch windows:

- ▶ Highlight the icon for the page you want to display and press .

To close a window:

- ▶ Highlight  in the top right corner for the page you want to close and press .

To go back a page:

- ▶ Highlight  and press .

To go forward a page:

- ▶ Highlight  and press .




To reload a page:

- ▶ Highlight  and press .

Open the Browser Options:

- ▶ From any open Web page, press **Options** (right softkey).

Options available within the browser menu include:


-    to change the display font size on the Web page.
- **Search the web** to launch a Web search.
- **Add this page to bookmarks** to store the address of the currently viewed Web page.
- **View all bookmarks** to display a bookmark list.
- **View browsing history** to display a list of the Web pages visited.
- **Save Image/Sound Data** to save the image or sound on the Web Page.
- **Send this page to a friend** to send a URL of the currently viewed Web page.
- **Overview Mode** to display the entire Web page.
- **Browser settings**
 - **Startup page** to change the default launch page.
 - **Automatic Overview Mode** to change the default view to overview mode.
 - **Default zoom size** to select the zoom value.
 - **Do not show images/Show images** to display or hide the images on the Web page.
 - **Icon row** to display or hide the area showing icons.
 - **Popups** to allow or block pop-ups.
 - **Clear private data** to delete the cookies, cache, history, or stored passwords.
 - **Advanced**
 - **Page information** to display information about the currently viewed page.
 - **Browser information** to display information about the browser.

- **Disable JavaScript/Enable JavaScript** to disable or enable Java scripting.
- **Disable error log/Enable error log** to set whether to save error logs (text files useful for debugging browser errors). To display the error log, select the **View error log** option from the submenu (available only when the error log is enabled).
- **Do not send referrer header/Send referrer header** to set whether to send HTTP URL referrer information.
- **Turn off redirect prompt/Turn on redirect prompt** to set whether to display a prompt when your data is being redirected.
- **Root certificate** to display the certifications.
- **Disable Virtual Mouse/Enable Virtual Mouse** to activate or deactivate the virtual mouse.
- **Virtual Mouse** to set the speed of the virtual mouse.
- **Reset browser** to reset all browser settings.

Info Portal

Visit the Public Mobile's home page. For further information on browsing, see [Browser](#).

Access the Info Portal

1. Press  > **Info Portal**.
2. Using the navigation key or softkeys, scroll through the available items.

Notes

- Instructions to perform tasks in this guide may change depending on the software version on your phone.

Copyrights

©2013 Kyocera Corporation. All Rights Reserved. Public Mobile, Everybody Talk and the Public Mobile logo are trade-marks of Public Mobile Inc. Other marks are the property of their respective owners. KYOCERA is a registered trademark of Kyocera Corporation.

This product contains NetFront Browser of ACCESS CO., LTD. ACCESS and NetFront are trademarks or registered trademarks of ACCESS CO., LTD. in Japan and other countries. This software is based in part on the work of the Independent JPEG Group.

The *Bluetooth*[®] word mark and logos are owned by the Bluetooth SIG, Inc. and any use of such marks by Kyocera Corporation is under license. Other trademarks and trade names are those of their respective owners.

T9[®] is a registered trademark of Nuance Communications, Inc. and its affiliates in the United States and other countries. Copyright © 2013 Nuance Communications, Inc. All rights reserved.

Index

- 3-Way Calling, 24
- Abbreviated Dialing, 17
- Airplane Mode, 36
- Alarm, 65
- Alerts, 34
- Auto Redial Mode, 25
- Auto-Answer Mode, 25
- Automatic Speech Recognition (ASR), 66
- Backlight, 30
- Battery, 8
 - Capacity, 8
 - Charge, 3
 - Install, 2
 - Remove, 9
- Bluetooth, 73
 - Icons, 10, 74
 - Make Your Phone Discoverable, 73
 - Menu, 74
 - Pair Devices, 74
 - Send Items, 76
 - Trusted Devices, 75
 - Turn On and Off, 73
- Brightness, 30
- Browser, 88
 - Menu, 89
 - Web Navigation, 88
- Calculator, 71
- Calendar
 - Add a To Do, 62
 - Add an Event, 61
 - Alerts, 62
 - Delete Events, 63
 - View Events, 63
- Call
 - 3-Way Calling, 24
 - Answer, 20
 - End, 21
 - Forward, 24
 - In-call Options, 20
 - Make, 15

- Phone Call Options, 23
- Settings, 25
- Call Answer Mode, 25
- Call Waiting, 23
- Caller ID, 23
- Camera, 77
 - Assign Pictures, 78
 - Camera Mode Options, 78
 - Settings, 80
 - Store Pictures, 81
 - Take a Picture, 77
- Clock
 - Display, 31
 - World Clock, 71
- Contacts
 - Assign a Picture to a Contacts Entry, 51
 - Assign a Ringer to a Contacts Entry, 50
 - Assign a Speed Dial Number, 53
 - Create a New Contacts Entry, 48
 - Delete a Contacts Entry, 50
 - Edit a Contacts Entry, 49
 - Find, 52
 - List, 47
 - Make a Call From, 16
 - Secret Entries, 54
- Countdown Timer, 72
- Customer Support, 4
- Data Services, 87
 - Browser, 88
 - Disable, 40
 - Enable, 40
 - Launch, 87
 - Net Guard, 41
 - Security Features, 40
 - Status and Indicators, 87
 - Web Navigation, 88
- Delete
 - Calendar Events, 63
 - Phone Content, 39
 - Recent Calls, 45
- Display Settings, 29
- Earpiece, 7
- Emergency Call, 18
- Enter Text, 12

- Abc Mode, 13
- T9 Text Input, 13
- Text Entry Options, 14
- Text Input Mode, 12
- Font Size, 32
- Forward a Call, 24
- Greeting, 31
- Headset, 36
- Hearing Aid Device
 - Compatibility (HAC) Mode, 36
- Icon Indication, 9, 43, 74, 87
- Info Portal, 91
- Key Functions, 7
- Language
 - Display, 32
 - Preset Messages, 59
- Location Services, 37
- Lock Code, 38
- Lock Your Phone, 38
- Make a Call, 15
 - From Contacts, 16
 - From Recent Calls, 16, 44
 - To a Number in a Message, 18, 59
 - To Emergency Numbers, 18
 - Using Abbreviated Dialing, 17
 - Using ASR, 67
 - Using Speed Dial, 16
 - Using the Phone Keypad, 15
 - Using the Plus (+) Code, 16
 - With Pauses, 18
- Menu
 - Navigation, 11
 - Style, 32
- Messages
 - Access Messages, 56
 - Callback Number, 58
 - Clear Envelope Icon, 58
 - Compose Messages, 55
 - Preset Messages, 58
 - Signature, 58
 - Threaded Messages, 56
- Messages Settings, 57
- Microphone, 7
- Multimedia, 84

- Downloaded, 85
- Photos, 84
- Preloaded, 85
- Navigation Key Shortcuts, 37
- Net Guard, 41
- Notification Pop-up, 30
- Phone
 - Illustration, 1, 6
 - Key Functions, 7
 - Lock, 38
 - Reset, 40
 - Set Up, 2
 - Turn On and Off, 8
 - Unlock, 38
- Phone Number
 - With Pauses, 18
- Picture ID, 31
- Pictures
 - Assign, 31, 51, 78
 - Send, 82
 - Store, 81
 - Take a Picture, 77
- Plus (+) Code Dial, 16
- Power Save Mode, 31
- Preset Messages, 58
- Receive a Call, 19
 - Answer, 20
 - In-call Options, 20
 - Mute the Ringer, 20
 - Reject a call, 20
 - Send to Voicemail, 20
- Recent Calls, 42
 - Call Timer, 45
 - Delete, 45
 - Details, 43
 - Icons, 43
 - List, 42
 - Make a Call From, 16, 44
 - Options, 43
 - Save a Number From, 44
 - Save the Information in, 44
 - Thread, 43
- Reset, 40
- Ringers, 33

- Assign, 50
- Mute, 20
- Roaming, 26
 - Data Roaming, 27
 - Icon, 26
 - Settings, 27
- Save
 - Number From Recent Calls, 44
 - Number Using Keypad, 49
 - Number With Pauses, 18
- Screensaver, 29
- Secret Contacts Entries, 54
- Security, 38
 - Data Services, 40
 - Delete Phone Content, 39
 - Lock Code, 38
 - Lock Phone, 38
 - Net Guard, 41
 - Reset Phone, 40
 - Unlock Phone, 38
- Set Up
 - Phone, 2
 - Voicemail, 3, 21
- Settings
 - Camera, 80
 - Display, 29
 - Phone Call, 25
 - Phone Setup Options, 34
 - Ringers, 33
 - Security, 38
 - Volume, 32
- Signature, 58
- Silence All, 33
- Simple Data Exchange, 59
- Speed Dial, 16
 - Assign Numbers, 53
- Stopwatch, 72
- TTY Mode, 35
- Turn Your Phone On and Off, 8
- Unlock Your Phone, 38
- Vibration, 37
- Voice Memos, 69
- Voice Services, 66
 - Automatic Speech Recognition (ASR), 66

- Voice Memos, 69
- Voicemail, 21
 - Check Messages While Roaming, 27
 - New Message Alerts, 22
 - Notification, 22
 - Retrieve Messages, 22
 - Set Up, 3, 21
- Volume, 32
 - Adjust, 33
 - Silence All, 33
- Wallpaper, 31
- Web, 87
 - Browser, 88
 - Launch, 87
 - Navigation, 88
 - Status and Indicators, 87
- World Clock, 71
- Zoom, 79