

# Content

Content.....	<b>Error! Bookmark not defined.</b>
1 Introduction.....	<b>Error! Bookmark not defined.</b>
1.1 Acknowledgement.....	3
1.2 Announcements.....	3
1.3 Safety Instruction.....	3
1.4 Abbreviation/Terminology.....	5
2 DEVICE Introduction.....	<b>Error! Bookmark not defined.</b>
2.1 DEVICE Operation and Preparation.....	<b>Error! Bookmark not defined.</b>
2.3 DEVICE Status and Reminder.....	<b>Error! Bookmark not defined.</b>
3 Quick Start Guide.....	<b>Error! Bookmark not defined.</b>
3.1 Keys Function.....	8
3.2 Startup and Shutdown.....	8
3.3 Open and Close the Screen.....	8
3.4 Usage of Touch Screen.....	9
3.5 Main Interface.....	10
3.6 Visit Application Procedures.....	13
3.7 USB Connection.....	13
3.8 Words Input.....	14
3.9 Application Technique.....	16
4 Basic Setting.....	<b>Error! Bookmark not defined.</b>
4.1 SIM Card Management Management.....	167
4.2 Wireless and Internet.....	17
4.3 Bluetooth.....	18
4.4 Data Usage Situation.....	<b>Error! Bookmark not defined.</b>
4.5 More.....	22
4.6 Contextual Model.....	27
4.7 Display.....	29
4.8 Storage.....	33
4.9 Battery.....	35
4.10 Application.....	36
4.11 Account and Sync.....	37
4.12 Location Service.....	<b>Error! Bookmark not defined.</b>
4.13 Security Setting.....	41
4.14 Language and Input Method.....	43
4.15 Backup and Reset.....	45
4.16 Date and Time.....	46
4.17 Fixed-time Startup and Shutdown.....	47
4.18 Assistance Function.....	48
4.19 Engineer Selection.....	48
4.20 About Tablet.....	49

5	Multi-Media .....	50
	5.1 Music.....	50
	5.2 Video .....	51
	5.3 Photo Gallery .....	51
	5.4 Camera .....	52
	5.5 FM Radio.....	53
6	Communication Function.....	58
	6.1 Phone.....	58
	6.2 Text Message.....	58
	6.3 Contact List.....	59
7	Internet .....	60
	7.1 Browser .....	60
	7.2 Email .....	60
8	Other Application Procedures .....	65
	8.1 Clock .....	65
	8.2 Calculator .....	65
	8.3 File Manager .....	66
	8.4 Recorder .....	69
9	Installation of Procedures.....	70
	9.1 Installation.....	70
	9.2 Uninstall .....	70
10	Troubles Shooting .....	74

# 1 Introduction

## 1.1 Acknowledgement

Thanks for your purchase of our product. MR706 is high definition tablet PC. Its CPU is MT8312、MTK8382, which apply the Cortex-A9, dominant frequency is 1GHz, it is based on Android 4.2.2 operation system, and easy to expand the third application procedure.

The product is designed with various functions, including WCDMA, WIFI, BT, GPS,FM, voice call and so on. It is easy to achieve wireless communication and internet, you have access to surf the internet anytime and anywhere; it is also built with high accuracy GPS module, so that it can be used for navigating through installing map software. There are many sensors which offer you brand-new operation and entertainment; besides, it has camera shooting, which leads electronic consumption to enter into a fresh palm internet entertainment time.

The manual systemically introduces the functions, use techniques and announcements, please read this manual carefully before your operation.

## 1.2 Announcements

### Preventive maintainance

- Please always keep the DEVICE dry. To avoid the device short trouble, corrosion fault and electric short, please prevent the device, battery and charger from water and moisture, and don't operate the device or charger by wet hand.
- To avoid failure of device, battery and charger, please prevent the device, battery, charger from violent shock or shake.
- To avoid failure of device, battery and charger, please prevent the device, battery, charger of all over heating or too cold circumstance
- Never shock, throw, prod the DEVICE, or drop, extrude, bend the DEVICE.
- Never disassemble the device and accessories arbitrarily, otherwise the device and accessories are not in our company warranty scope.

## 1.3 Safety Instruction

Before the operation of the DEVICE, please read this chapter and teach your kids about these information. For further details, please refer to the safety instructions and announcement.

- Never use the DEVICE when driving car, in order to ensure safe driving.
- In the medical area, please abide by related rules and regulations. Please shut down the DEVICE when it is near to the medical area.
- To avoid the wireless signal to interrupt the plane- controlled signal, please shut down the DEVICE or using airplane mode when you are boarding a flight,
- To avoid electronic equipment failure, please shut down the DEVICE in the vicinage of high-accuracy electronic equipments.
- Please don't disassemble the DEVICE and accessories. Only authorized agent has access to service the DEVICE.
- Please keep the DEVICE far away from magnetic equipments, the radiation of DEVICE may erase the data stored in the magnetic equipments.
- Never use the DEVICE in the vicinage of high temperature, inflammable gas ( gas station).
- Protect the DEVICE and accessories from kids reach scope, and avoid the kids to use the DEVICE without parents' supervision.
- Please comply with related rules and regulations, and respect others' privacy and legal rights while using the DEVICE.
- Please strictly adhere to related instructions in the manual when using USB cable to ensure the safety of the DEVICE or PC.
- Never use the DEVICE in bathroom or other hudevice environment, and please protect the DEVICE from liquid wash or wet.

## 1.4 Abbreviation/Terminology

Abbreviation/Terminology	Full Name	Description
DEVICE	Mobile Internet Device	Mobile Internet Terminal
WIFI	Wireless Fidelity	Base on IEEE 802.11b standard wireless LAN
T F	TransFlash	Alternative name Micro SD,super miniature memory card

## 2 DEVICE Introduction

### 2.1 DEVICE Operation and Preparation

#### Battery Charging











If this navigator is first used, please use AV adaptor to fully charge it.

1. Apply the power adaptor to charge for DEVICE.

### 2.2 DEVICE Status and Reminder

#### Reminder icons

When some remind message appears in your reminder window, please click column and slip the screen to open the reminder list. Choose the menu you need, and confirm the information. Then you can close the reminder window through clicking the column to slide up. Please refer to below status icons:

	New email		Airplane Mode on
	USB connected		USB debugging connected
	Return button		Downloading
	Display recently-used application		Home button
	Current electric volume.		WIFI connected, internet is available

**Reminder board**

Reminder icons will work while receiving emails, WIFI is open, you can open the reminder board to view the detailed information.





**Open the reminder board**

When the reminder column shows new reminder icon, please hold the column and slip down your finger, then the reminder board is opened.

## 3 Quick Start Guide

### 3.1 Keys Function

#### Keys Function Description:

Power button	Short press to sleep/wake up, long press to startup and shutdown.
Volume + (up)	increase the volume
Volume - (down)	decrease the volume
<b>HOME button</b> (home) 	Click it in any interface will return to main interface.
<b>Back button</b> (back) 	click it in any interface will return to previous menu
<b>Menu button</b> 	This button will display in menu interface.
<b>Setting button</b> 	display recently browsed history

### 3.2 Startup and Shutdown

#### Startup

Long press **POWER key for three seconds**, you can enter into startup picture. The system enters into screen lock status, please unlock it.

#### Shutdown

1. Long press POWER, it will popup shutdown window.
2. Shutdown window contains mute mode, airplane mode, reboot mode and shutdown four options.
3. Click Shutdown is the last step.

### 3.3 Open and Close of the Screen

**Screen will be closed on its own when no operation happens.**

1. Screen will be closed on its own if no operation happens for some time to save battery




power

2. When screen is open, press POWER key, the screen will be closed immediately.

**Open the screen when it is closed.**

If the screen is closed, short press POWER to open the screen. The screen will be locked open it, it will show the picture as below picture, left slide to unlock and enter into camera, right slide the unlock icon to unlock the screen.



**Picture 3.1**

## **3.4 Usage of Touch Screen**

### **DEVICE operating methods**

There are below methods to view the main screen, menu and application procedure in your DEVICE.

#### **Click**

When you want to use the screen keyboard typing or choose application in the main interface, you only need to touch it by your finger.

#### **Press on**

If you want to open some item( textbox or the link in the webpage), or shortcut and main procedure move, you can press on this item.

#### **Quickly slide or slide**

Quickly slide or slide indicates make quick vertical or horizontal movement by finger.

### **Pull**


Before you pull, you need to hold it with strength until you pull it into the position you want.

### **Rotate**

For most pictures, you only need to rotate the DEVICE sidewise to change the screen direction from horizontal to vertical. For instance, when you are typing words, and watching movies.

## **3.5 Home Page**

Main interface as below picture 3.2, long press the blank and it will popup windows to set wallpaper, folder, widgets, and shortcut.



### **The extended home page**

The home page can be extended beyond the width of screen to provide more space, which you can put new-added shortcuts and widgets. Click the blank space in home page then slide right or left to extend to the right or left of the screen. In the home page, there are two extended pictures, as Picture 3.3.



Picture 3.3

### The shortcut icons management in desktop application.

#### Create folder icon in desktop

1. Drag the icons need to be put together on one icon(can also overlay several icons)as Picture 3.4.
2. Then click the overlaid icons, the applications can be folded, as Picture 3.5.

Click the unnamed folder in the black box, it will popup the hidden keyboard, the folder name can be renamed (this is similiar with Apple IOS system), the icons position can be changed through long press.



**Picture 3.4**



**Picture 3.5**

### **Remove the icons in desktop**

1. Long press the icons need to be remove, then on the right above of the screen, it

will appear



icons.


2. Drag the icon to the above of the remove icon, till the icon become red, then move your finger to delete the icon.

### **Change the wallpaper of desktop**

1. In home page, long press any blank space in main screen, it will popup a window to change the wallpaper.
2. Click the gallery or wallpaper gallery to select the wallpaper.



### 3.6 Visit Application Procedures

Click  in right top of Picture 3.2, enter into main interface as Picture 3.6, choose the application procedure you want to visit.



Return to  
home page

Picture 3.6

### 3.7 USB Connection

#### DEVICE storage configuration

Before transmitting documents, you have to conduct storage configuration for your DEVICE:

1. Connect the DEVICE and computer by USB cable, the reminder column will show the remind information.
2. Open the reminder board; please view the DEVICE status and reminder to learn how to open the board.
3. In the reminder board, click the “USB Connected”, it will as below Picture 3.4, then click “open USB storage configuration”.
4. Now the USB is connected successfully.



Picture 3.7

#### Copy the document into memory card

1. Connect the DEVICE to computer with USB cable.
2. As DEVICE storage configuration, it is connected with computer successfully.
3. Open the “My computer” in your computer, check the items in “removable disc”.
4. Copy the documents you need into “removable disc”.
5. After copying finishes, click “shutdown the USB storage configuration” to uninstall.

Notice: When the DEVICE is connected with USB cable, and you open the USB storage configuration, you can't view the memory card through the DEVICE. Only after you detach the USB cable, you can view the memory card in the DEVICE.

## 3.8 Typing words

#### Use the screen keyboard

When you start the procedure or choose the words or numbers edition, it will show the screen keyboard. The keyboard contains below typing options:


1. Android keyboard
2. Google Pinyin

#### Choose the typing method you want

1. Click Setting pocedure application.

2. Click Language and Keyboard.
3. In the text setting area will reveal all the installed words-typing methods in your DEVICE.
4. Tick the typing method you want.

### Use and switch of input method



Picture 3.8

1	switch the capital and small letter
2	switch the mode of words input
3	click to insert the space
4	click input to enter
5	delete the character in the left of cursor, click and hold to delete all the characters in the left of the cursor.

## 3.9 Operation Technique

### Enter widgets interface

In the application interface, click widgets on the above of screen, or slide the screen, it will switch into widgets interface. Long press any widget to create its shortcut, then you can enter into the application through the shortcut icon.

### Create application shortcut icons in the desktop

In the application interface or widgets interface, long press any icon to switch into desktop automatically, drag and hold the icon, you can move to any position in the desktop.

# 4 Basic Setting

## 4.1 SIM Management

### 4.1-1 Voice call


Click settings in main menu, choose SIM Management, as Picture 4.1



Picture 4.1

Click voice call, choose defaulted SIM card, as Picture 4.2






**Picture 4.2**

#### 4.1-2 Video Call

Click settings in main menu, choose SIM Management, and click video call, choose defaulted SIM card when makes video call, as Picture 4.3



**Picture 4.3**

#### 4.1-3 Message

Click settings in main menu, choose SIM Management, click message, choose the defaulted SIM card when sends message.

#### 4.1-4 Data Connection


Click setting application in main menu, choose SIM management, click data

connection, choose the defaulted SIM card.

## 4.2 Wireless and Internet

### 1. Connect Wi-Fi

- 1) In the main menu or interface, choose **setting** application procedure.
- 2) Click WLAN, open wifi, device will automatically search the available Wifi wireless internet.
- 3) Choose the Wi-Fi internet you want to connect, if it has password, it will pop up the password window, enter password, click connect.





Picture 4.6

### 2. Add Network

- 1) Click “+” icon in right top
- 2) Input network SSID, the wireless network name, click save.
- 3) Click user name already saved, click connect to use network **Network Notice**  
If you open Network Notice, when WIFI signal appears, the right bottom will remind you available WLAN network.

### 3. Keep WI-FI on during sleep.


1. Click  icon in right top, select **advanced**.
2. Click **Keep WI-FI on during sleep**,




Picture 4.9

## 4.3 Bluetooth

### Bluetooth function operation


1. Click setting application in main menu interface
2. Click bluetooth and open it.
3. Click the available Bluetooth device, it will popup request window, enter into related password, and match the device to connect.
4. After match successfully, choose the operation you want to, click  to enter into Picture 4.11.



Picture 4.11

### Bluetooth setting

#### 1. Rename tablet

Click  icon in right top select rename tablet, you can rename it as you want

#### 2. Check visibility timeout


Select **visibility timeout setting**, choose the time you want to set.

3 Display the file you received

3. Choose display the file you received, you can view download and upload files. Open Bluetooth distance induction device, when two Bluetooth devices distance is quite far or connection is cut off, the Bluetooth will remind you with sound.


## 4.4 Data Usage


Check SIM card data usage, as Picture 4.15



Picture 4.15

Check WIFI data usage

Click  icon in right top of Picture 4.15, click **Data Usage**, as Picture 4.16



Picture 4.16

## 4.5 More

### 4.5-1 Airplane Mode


Airplane Mode can turn off WIFI and GSM card function quickly, when airplane mode is turned on, WIFI and GSM can't get any signal, then airplane mode is turned off, WIFI and GSM

module will recover to previous state.

#### 4.5-2 VPN

Open VPN, click **add VPN network**, Input **name** and server address, then save.

Click VPN, as Picture 4.18, input VPN user name and password, click connect.




Picture 4.18

#### 4.5-3 Network sharing and portable hotspots

Portable WI-FI hotspots

1. Click setting application in main menu.
2. Click more when wifi is well connected, open network share and portable hotspot






Picture 4.19



Picture 4.20

3. Click **keep WI-FI hotspots on**, choose open time.
4. Return to previous menu, open portable WLAN hotspots, click configure WI-FI hotspots.




Picture 4.21

5. Set passwords you want to, password should be more than 8 numbers.

#### 4.5-4 Mobile Networks

##### 1. 3G service


Click 3G service, as Picture 4.22, choose available defaulted SIM card, GSM is 2G network, WCDMA is 3G network.



Picture 4.22

2. Access Point Name( APN)


Click **mobile network**, as Picture 4.23



Picture 4.23

Choose access points name (APN), choose SIM card you need to connect,  
Choose connect type, as Picture 4.24





**Picture 4.24**

Remark: (CMWAP transmitters data through GPRS, the webpage it visit belongs to wap webpage, and CMNET support www browse mobile phone network, it can also log in webpage in computer. And the charges are also different.)

#### **4. Network Operator**

Click network operator, choose SIM card you need to connect, system will search available GSM and WCDMA network, as **Picture 4.25**



**Picture 4.25**

#### **4.5-5 GPRS data prior mode**

After Open GPRS data prior mode, systems will priority chooses your network.


## 4.6 Contextual Model

1. Open settings, click contextual model, as Picture 4.26,



Picture 4.26

2. Click **standard** to enter into Picture 4.27




Picture 4.27

1. **Vibrate**

In picture 4.27, click **vibrate**, DEVICE will vibrate when someone calls you.

2. **Volume**


In picture 4.27, click volume, you can set ringtone, notice, and alarm volume, as Picture 4.28



Picture 4.28

### 3. Voice call Ringtone


In picture 4.27, click **voice call ringtone** to choose voice call ringtone, as Picture 4.29



Picture 4.29

### 4. Video call ringtone

In Picture 4.27, click video call ringtone to choose video call ringtone, as Picture 4.30




Picture 4.30

(Note: Except standard, silent, meet, outdoor are only for selection, they can't be set.)

## 4.7 Display

### 4.7-1 Adjust the screen brightness

1. Click **Setting** application procedure.
2. Click **display**, choose brightness,
3. Drag the portlito to adjust the brightness volume.As Picture 4.31



Picture 4.31

4. Click OK after brightness is adjusted.

#### 4.7-2 Wallpapers

1. Click **setting** application.
2. Click **display**, click **wallpaper**.
3. You can choose different wallpapers as you like—live wallpapers---gallery(user defined)---wallpapers (system defect)---video wallpaper, **as Picture 4.32**




Picture 4.32

#### 4.7-3 Auto rotation

System is defaulted as open auto rotation, when it is turned off, system won't rotate DEVICE screen by G-sensor.

#### 4.7-4 Sleep


1. Click setting appliation.
2. Click display.
3. Click sleep.
4. Set the sleep time as you want, **as Picture 4.33**



Picture 4.33

#### 4.7-5 Font size


Click **font size** to adjust the font size, as **Picture 4.34**



Picture 4.34

#### 4.7-6 HDMI setting

1. Use HDMI connector, in the right bottom of DEVICE, it will remind HDMI connector is connected.
2. Click HDMI setting, as Picture 4.35



**Picture 4.35**

(1) Audio


Open audio to realize HDMI audio output.

(2) Never

Click never, DEVICE will never sleep.

(3) Video Resolution

Click video resolution to adjust resolution, as Picture 4.36




**Picture 4.36**



#### (4) OSD position setting

Click **OSD position setting**, DEVICE will adjust OSD position setting, as Picture 4.37



Picture 4.37

## 4.8 Storage

Open setting function, click memory, click **preferred install location**, you can choose install new application to choose preferred install location.

Check SD card and DEVICE storage space.

1. Enter into setting application.
2. Click storage, check storage space.
  1. Internal storage

#### (1) System storage

System storage is the space DEVICE leave for system file, as Picture 4.38. it can't be viewed.





Picture 4.38

## (2) Internal storage


Internal storage is DEVICE local NAND storage, as Picture 4.39, if you need to check the storage content, you can check it in main menu.



Picture 4.39

## 2. SD card

You can check storage space, SD card available space, unmount SD card and erase SD card, as Picture 4.40



**Picture 4.40**


Safely remove SD card

1. Click setting application.
2. Click memory.
3. Click uninstall SD card.
4. Now you can remove SD card safely.

**Note:** Removing SD card safely can protect SD card and increase its lifetime.

## 4.9 Battery


Click setting function, select battery, you can view the battery situation, as Picture 4.41



Picture 4.41


## 4.10 Application program

1. Click setting application in Apps.
2. Select application, after enter, you can manage and delete installed application and check system used storage space and left space. (As Picture 4.42)



Picture 4.42

3. View internal storage used space and left space, as Picture 4.43



Picture 4.43


4. View the working device, used space and available space, as Picture 4.44



Picture 4.44


## 4.11 Account and Sync

1. Select setting application
2. Open account and sync, as Picture 4.45




Picture 4.45

3. Click **add an account**, as Picture 4.46



Picture 4.46


4. After successfully load, it will open the sync function, as Picture 4.47



Picture 4.47

## 4.12 Location service

Click **setting**, select **location service**, as Picture 4.48



Picture 4.48

### 1. Google's location service

Open Google location service, you can use WIFI to positioning DEVICE.

### 2. GPS satellites



Open GPS satellite, you can use GPS to positioning DEVICE.


## 4.13 Safety setting

### Set locked screen

Lock the touch screen by unlock icon or password to protect your device.

### Set unlocked picture

1. Click setting application in main interface.
2. Click **safe**.
3. Click **locked the screen**.
4. Choose **picture** in text setting area.
5. Click next following the remind message.
6. The unlocked pattern board pop up, there are nine touch spots, connect 4 points from vertical, horizontal or diagonal direction. As Picture 4.10, move your finger from the screen when finish. The system will record your new unlock pattern.
7. Click **continue**.
8. When you see the reminder, enter the unlock pattern, then click **confirm**.



Picture 4.53

### Set unlock PIN code

1. Click **setting** application in main interface.
2. Click **safe**.

3. Click **screen locked**.
4. Choose **PIN** in text setting area.
5. Enter new PIN code(numbers) and click **continue**.
6. Enter new PIN code again and click **confirm**.

#### Set unlock password

1. Click **setting application** in main interface.
2. Click **safe**.
3. Click **screen locked**.
4. Set password in text setting area.
5. Set new password(letters and numbers) and then click **continue**.
6. Enter the password again and then click **confirm**.

#### Unknown source

1. In main interface, click **setting**.
2. Click **safety**.
3. Click **unknown source**, as Picture 4.54




Picture 4.54

Note: Manual installing APK files needs to turn on unknown source.

## 4.14 Language and Input Method


Click setting, select language and input method, choose language to switch language, as






Picture 4.55

Click **setting**, choose **language and input**, choose **Android keyboard setting**, click input language, as Picture 4.56




Picture 4.56

Choose the language you want to change in the language list, as Picture 4.57



Picture 4.57

Return to **language and input method**, click **default**, as Picture 4.58, select input method you want to use




Picture 4.58

## 4.15 Backup and Reset

Connect WIFI and login your Google account, choose **backup my data**, system will back up your data into Google server.

If you need to recovery factory reset, please click reset, as Picture 4.59, if you

need to formulate NAND, please click reset tablet.




Picture 4.59

## 4.16 Date and Time

According to the preset, system will voluntarily apply the date, zone, and time provided by internet.

Manual set date, time and zone

1. Click Setting application procedure.
2. Slide down the screen, then click **date and time**.
3. Turn off “auto setting of date and time”.
4. Turn off “auto setting zone”.
5. Click Zone Selecting, then choose the zone lists. Slide down the list to view more zones.
6. Click **Date setting**, then click upper or down button to adjust date, month, and year, click **setting** when you finish selection.
7. Click **Time setting**, then click upper or down button to adjust hour and minute, click AM or PM to change morning or afternoon ( there is no such selection when you see 24-hour format). Click **Setting** to finish.
8. Click **24-hour format**, switch between 12-hour or 24-hour format, the time format you choose will be used on the alarm clock.
9. Click date format setting, then choose the time format you want to show on device.



Picture 4.60


## 4.20 About Tablet


Check device state

1. Check **Setting** application.
2. Click **about tablet**, check **state message**, **model**, **Android version**, **version No** and so on.
3. Click **state message**, check **battery state**, **battery volumne**, **SIM state**, **IMEI number**, **IP address**.


# 5 Multi-Media

## 5.1 Music

Enter into music player: in menu or desktop click music  icon to enter into music player, click the music you want to play, as Picture 5.1:




Picture 5.1




Picture 5.2

- Drag the progress bar to adjust play progress.
- Operation of music player button as Picture 5.2

## 5.2 Video

- Enter video player: choose  application in main menu, choose the video you want to play.
- Operation of video player button as Picture 5.3



Picture 5.3

## 5.3 Photo Gallery

**Photo gallery** application can auto search photos and video files in SD card, and photo gallery will classify these photos and videos in folder. You can apply photo gallery to view and edit photos, set the photos as wallpaper and watch the video.

### View pictures

1. Click gallery application in main interface.
2. Enter into gallery, click the folder you want to view.
3. Click the picture you want to view, the system will play it in full screen mode automatically.
4. The pictures can be zoom in and zoom out, put two fingers on the screen, the

separate the fingers (gather up the fingers, the picture will be zoom in) or double click the screen.


Note: when you browse the pictures, slide left or right to view more pictures.

### Edit and set pictures

When check the pictures in full screen mode, click menu key to display menu selection, you can choose the selection you need to edit and setting pictures.


- **Edit**
  1. Click **menu** key, display the menu selection.
  2. Click **edit**.
  3. Adjust the brightness, style, color, antialias setting in selection.
  4. Click **save**.
  5. If you want to give up edit, click **return** key, click **not** to return to picture browse.

## 5.4 Camera

In the main interface or desktop, click camera application procedure  , enter into camera


- Operation of camera ,Switch camera: choose **Menu** key, click **switch front/back camera**.

## 5.5 FM Radio

Click  in the main interface or desktop to enter into FM radio interface:

- Radio button operation

Click search to search FM band

- Save channels: Click  button in the main interface to save the channel, and the channel will be saved in channels list.



Note: You need to insert earphone as antenna when using FM radio

## 6 Communication Function

### 6.1 Phone


- 1 Click **Phone** application procedure
- 2 Operate as Picture 6.1




Picture 6.1



## 6.2 Text Message

1 Enter into main menu, choose  application procedure.



2 Click “Edit new message”



Picture 6.2


## 6.3 Contact List

Click Contact list  in the main interface.

- Search contact: click  button, enter into search function
- Add contact: click  button, enter into add contact interface.


# 7 Internet

## 7.1 Browser

In case of Wi-Fi or mobile internet is click browser  in the main menu or desktop to enter the browser interface.


## 7.2 Email

**Email** application procedure contains email setting guide, you can add the external POP3 OR IMAP email account of normal web email service provider (For instance, Yahoo, Gmail, Hotmail etc.)



Picture 7.2

### a. Email Setting

1. After you click the sending email icon , you can see the email setting guide, which can help you to set.
2. Input your email address and password.
3. Click “Next step” button, choose your email type is POP3 or IMAP.
4. Click “Next Step” button to check whether the email box servicer can receive or send emails
5. Input the email account and display the email subject, and click **finish**.

6. If the email box is available, you will enter into your mail box automatically.



#### b. Delete the email account


You can delete setted POP3 or IMAP email account from your DEVICE.

Click .

1. Enter into your mail box.
2. Press Menu key.
3. Click Account
4. Press the account you want to delete.
5. Click confirm to remove.

#### c. Send E-mail

1. Click  to display your mail box.
2. Click the inbox, it will refresh the new emails automatically; click it to read new email.
3. Press Menu key. Menu will popup.
4. Click **Edit**  to enter into new email editing interface.
5. Input the receiver's email address.
6. Input the subject and email content.
7. If you want to add attachment, click menu key, the menu popup.
8. Click "Attach file" (photo, music, video, contacts).
9. Click "send" to send the email out.



Picture 7.3

## 8 Other Application Procedures

### 8.1 Clock

Click **Clock** procedure, enter into below interface.

There are clock, picture, music and homepage buttons.




Picture 9.1

### 8.2 Calculator




1. Click
2. Enter into the basic board of calculator.
3. Soft touch the numbers or operator in calculator to calculate.




Pictuer 9.2

## 8.3 File Manager

File manager will copy, cut, delete, rename the documents or the folder in the TF card, it also will share the files, install apk etc.

In the main menu or desktop, click the document manager icon  to enter into documents manager.





Picture 9.3


a、 Copy, cut, delete, rename the files and folder: choose the file or folder, long press the file or

folder to enter into the interface as Picture 9.4, you can operate the file or folder.




**Picture 9.4**

b、 Paste the copy or cut file: choose the file you want to paste, choose right top  icon to enter into Picture 9.5, choose right top  icon to enter into Picture 9.6




**Picture 9.5**



**Picture 9.6**


C. Share file: choose any file, long press it, it will popup “share”, choose the share way you want in the list



**Picture 9.7**

d. Install apk file: Choose the file suffixed .apk in the file manager, you can install the third part software as reminder.



e、Build new folder: Choose the menu you want to build the file, click  icon in right top, choose new folder, you can build new folder as reminder.

## 9 Installation of Procedures

### 9.1 Installation

#### Install the third party application procedure

1. Click “file manager” application procedure; choose the application procedure you need to install.
2. Hold the application procedure you need to install.
3. A popup **install** will appear, **click install apk**.
4. Finish the installation as guide, it will operate.

### 9.2 Uninstall

#### Uninstall application procedure

1. Click setting icon in main interface.
2. Click **manage application procedure**, list all the application procedures installed in the system.
3. Click the APK you want to uninstall, click **uninstall**.
4. Click **confirm** to finish uninstallation.

## 10 Trouble Shooting

### 1. The first startup of DEVICE is slow

After the DEVICE system upgraded, the first startup need to install the pre-installed application software, the lead time is around 2-3 minutes, the startup afterwards will be much quicker.

### 2. DEVICE can't connect Wi-Fi

- Make sure the wireless router of internet service can work in normal.
- Ensure the DEVICE and wireless router in certain distance, and no wall or

other barrier between them.

- Ensure the user name and password both correct.

### **3. DEVICE feels hot**

When many application procedures are used in meanwhile, or the brightness of screen open to the lightest or under charging, DEVICE may feel fever. It is normal.

### **4. Email can't be set or Registration of application procedure.**

- Ensure your internet is well connected.
- Make sure your email setting way is correct.
- Keep your system time and local time consistent.

### **5. The system is abnormal and can't work.**

When you install some third party application procedure, it may cause abnormal work, you can press **Reset key**(next to power port) to reset the system.

### **6. The webpage can't be opened**

- Please keep the distance between from route to DEVICE in effective range.
- Please restart WIFI and try again.

### **7. Device works terribly slow sometimes**

It is normal phenomenon. Please turn off some application you don't need in advanced task management, or uninstall some third party application to release more system resource.